



Philips Hue
Dimmer switch

Wireless installation

Easy access to light scenes
Smooth dimming
Use as a remote control



046677473372

Control your lights

anywhere in your house

Control and dim your lights with a Hue dimmer switch. Both a wall switch and remote control, this smart switch attaches easily to walls with the included adhesive and can be removed from the magnetic base to use as a remote control.

Limitless possibilities

- Brighten and dim your smart lights
- Switch between light scenes
- Connect up to 10 smart lights
- Mount the dimmer switch anywhere

PHILIPS

Dimmer switch

Wireless installation Easy access to light scenes, Smooth dimming, Use as a remote control

Specifications

The switch

- Batteries included: 1 x CR2450
- Frequency band: 2400 – 2483.5 MHz
- Lifetime: 50000 clicks
- Max. lights per switch: 10 if not linked to Hue bridge
- Minimal battery lifetime: 3 year(s)
- Minimal range indoor: 500 inch
- Software upgradeable: when connected to Hue bridge
- Switch depth: 0.43 inch
- Switch height: 3.6 inch
- Switch width: 1.38 inch
- Weight of switch: 37 g
- Wall plate depth: 0.55 inch
- Wall plate height: 2.76 inch

- Wall plate width: 4.5 inch
- Weight including wall plate: 67 g
- Zigbee Light link: protocol IEEE 802.15.4

What's in the box

- Hue dimmer switch: 1

Environmental

- Operational humidity: 5% < H < 95% (non condensing)
- Operational temperature: -10°C – 45°C

Guarantee

- 2 years

046677473372

Highlights

Brighten and dim your lights



The Philips Hue Dimmer switch allows you to wirelessly turn your lights up high or down low.

Switch between light scenes



The smart Dimmer Switch allows you to toggle through four light recipes by simply pressing the "on" switch. Energize, Concentrate, Read, and Relax are programmed by default and you customize your selection in the Hue app.

Connect up to 10 smart lights



With the Philips Hue wireless dimmer switch, you can connect up to 10 lights to control simultaneously from a single dimmer switch.

Mount anywhere



The Philips Hue Dimmer switch functions as a normal wall switch and dimmer — but better. In addition to mounting with screws or strong adhesive tape, you can remove the magnetic control and carry it with you anywhere.



Issue date 2019-03-14

Version: 4.0.1

12 NC: 9290 011 73661

© 2019 Philips Lighting Holding B.V.
All Rights reserved.

Specifications are subject to change without notice.
Trademarks are the property of Philips Lighting Holding B.V. or their respective owners.

www.philips.com