

## Discover Your Phone



*Philips continuously strives to improve its products. Therefore, Philips reserves the rights to revise this user guide or withdraw it at any time without prior notice. Philips provides this user guide "as is" and does not accept, except as required by applicable law, liability for any error, omission or discrepancy between this user guide and the product described. The device is meant to be connected to GSM/GPRS networks.*

## How to ...

<b>Switch the phone On/Off</b>	Long press and release  .
<b>Enter your PIN code</b>	Enter your PIN code using the keypad and press  to confirm.
<b>Make a call</b>	Enter the phone number using the keypad and press  .
<b>End a call</b>	Press  .
<b>Answer a call</b>	When the phone rings, press  .
<b>Activate/deactivate handsfree mode</b>	In idle mode, enter the phone number using the keypad or select a contact in the phonebook. During a call, press  to activate the handsfree mode. When there is an incoming call, Press  <i>Options</i> , then select <i>Accept with handsfree</i> and press  .
<b>Mute a call</b>	When the phone rings, press  .

<b>Reject a call</b>	When the phone rings, press  .
<b>Adjust conversation volume</b>	Press volume side keys to adjust the volume during a call.
<b>Adjust ringer volume</b>	When the phone is in idle mode, press  > <a href="#">Settings</a> > <a href="#">Sounds</a> > <a href="#">Ring volume</a> to adjust the ring volume of an incoming call.
<b>Access all calls list</b>	Press  in idle mode.
<b>Access Shortcuts</b>	Press  in idle mode.
<b>Access Contacts</b>	Press  in idle mode.
<b>Access <a href="#">Create message</a></b>	Press  in idle mode.
<b>Access <a href="#">My files</a></b>	Press  in idle mode.
<b>Access Main Menu</b>	Press  in idle mode.

<b>Access <a href="#">Calendar</a></b>	Press  in idle mode.
<b>Go to previous menu</b>	Press  <a href="#">Back</a> when browsing menu or in editing mode.
<b>Quickly return to idle when browsing menus</b>	Short press  .

## Softkeys

The left and right soft keys ( and ) are located at the top of keypad area. Pressing the soft keys allows you to select the option displayed on the screen directly above them, including options during a call. The functions of the soft keys change according to the current context.

## Operations of the headset

The following operations are applicable to headsets with only one key. When you enter a phone number in idle mode, short press the headset key to dial the number. To

stop dialling, long press the headset key.  
 During a call, short press the headset key to record or stop recording; long press to hang up the phone.  
 When there is an incoming call, press the headset key to answer the call; long press to reject the call.

## Main Menu

You can access the different features of your X600 phone from the main menu. The following table summarizes the structure of the main menu, what the icons represent and the page number on which you can obtain more information regarding the menu functions.

<i>Entertainment</i>  page 21	<i>Browser</i>  page 22	<i>Media player</i>  page 25
<i>Camera</i>  page 28	<i>Messages</i>  page 33	<i>My files</i>  page 47
<i>Business</i>	<i>Contacts</i>	<i>Profiles</i>

 page 52	 page 58	 page 61
<i>Connectivity</i>  page 63	<i>Calls</i>  page 66	<i>Settings</i>  page 70

Press  in idle mode to access the main menu, and press , ,  or  to navigate through the icons and lists. When navigating through a list, the scrolling bar on the right of the screen will indicate your current position in the list. Press  *Select* to access the corresponding options of the selected item in the list. Press  *Back* to return to the previous menu.

## Menu without SIM

If you do not have a SIM card, those menu items whose functions that cannot work without a SIM will be greyed out and not accessible.

# Table of contents

1. Getting Started .....	6	Pinyin Input .....	17
Inserting the SIM card .....	6	Stroke input .....	18
Switching on the phone .....	7	4. Entertainment .....	21
Charging the battery .....	8	Games .....	21
Insert a micro SD Card .....	9	JAVA .....	21
Setting hotkeys .....	9	5. Browser .....	22
2. Calling .....	11	WAP .....	22
Switch on the phone .....	11	Push Inbox .....	24
Switch off the phone .....	11	6. Media player .....	25
Make a call .....	11	Music player .....	25
Speed dial .....	12	7. Camera .....	28
Answer and end a call .....	12	Camera .....	28
Options during a call .....	12	Video recorder .....	30
Make a second call (Network dependent) .....	13	8. Messages .....	33
Make a Conference Call (Network dependent) .....	13	Create message .....	33
Answer a second call (Network dependent) .....	14	Inbox .....	35
Contact Picture .....	14	Sent .....	37
3. Text and number entry .....	15	Outbox .....	38
Input method .....	15	Drafts .....	39
T9® English input .....	15	My favourites .....	39
Basic text input .....	16	Spam box .....	41
		SIM archive .....	41

Templates .....	41	View contacts .....	59
E-mail .....	41	View group .....	59
Advanced .....	43	Special numbers .....	60
Voice mail .....	44	Advanced .....	60
Settings .....	44	<b>12. Profiles .....</b>	<b>61</b>
<b>9. My files .....</b>	<b>47</b>	<b>13. Connectivity .....</b>	<b>63</b>
Pictures .....	47	Bluetooth .....	63
Sounds .....	49	USB function .....	64
Videos .....	50	Using PhilipsPhoneTools .....	64
Others .....	51	<b>14. Calls .....</b>	<b>66</b>
Memory status .....	51	View calls .....	66
Memory card .....	51	Call options .....	66
<b>10. Business .....</b>	<b>52</b>	Clear history .....	69
Calendar .....	52	<b>15. Settings .....</b>	<b>70</b>
Alarm .....	53	General .....	70
Calculator .....	53	Display .....	72
Voice recorder .....	54	Sounds .....	73
Memo recorder .....	54	Connectivity .....	73
Stopwatch .....	55	<b>Icons &amp; Symbols .....</b>	<b>75</b>
Countdown .....	55	<b>Precautions .....</b>	<b>77</b>
Unit converter .....	55	<b>Troubleshooting .....</b>	<b>82</b>
Firewall .....	55	<b>Philips Authentic Accessories .....</b>	<b>84</b>
Task .....	56	<b>Trademark Declaration .....</b>	<b>85</b>
STK .....	57		
<b>11. Contacts .....</b>	<b>58</b>		
New contacts .....	58		

Specific Absorption Rate Information ....	86
Limited Warranty .....	87
Declaration of conformity .....	90

# I. Getting Started

---

*Please read the safety instructions in the "Precautions" section before use.*

---

Before you start using your phone, you must insert a valid SIM card supplied by your GSM operator or retailer. The SIM card contains your subscription information, your mobile telephone number, and a small quantity of memory in which you can store phone numbers and messages (for more information, see "Contacts" on page 58).


You can also insert a memory card. This provides you with expanded memory capability, which allows you to store additional music, photo, and video files that are separated from the phone's built-in memory.

## Inserting the SIM card

---


### **Remove the back cover**

To insert the SIM card, you must first remove the back cover. As shown, press on the back cover with your thumbs and slide the cover. Then use your free hand to lift up the back cover.



### **Remove the battery**

Put your finger at the top of the battery and lift the battery up from its slot.




---

*You may lose all your personal settings if you remove the battery when the phone is switched on.*

---

### **Insert the SIM card**

Make sure that the clipped corner of the SIM card is facing the correct direction (clipped corner at upper left) and the metallic contacts are facing downwards. Slide the SIM card into the card slot until it stops. When you remove your SIM card the first time, make sure that you smoothen the edges, otherwise you may have difficulty sliding in the card.



### **Replace the battery**

With the metallic contacts facing downwards, press the battery down into its slot until it locks into place.



### **Replace the back cover**

Replace the back cover by sliding it down into its slots, until it stops.



---

**When inserting the battery, be careful not to damage the metallic connectors of the SIM card slot.**

---

### **Switching on the phone**

To switch on the phone, long press and release the  key. Enter the PIN code if required (the 4 to 8 digit secret code of your SIM card). It is preconfigured and provided to you by your network operator or retailer.

For more information on PIN code, see "Security" on page 71.

---

*If you enter an incorrect PIN code 3 times in succession, your SIM card will be blocked. To unblock it, you must obtain the PUK code from your network operator.*

---

## Charging the battery

---

Your phone is powered by a rechargeable battery. The new battery is partially charged. A sound alert will be emitted to warn you when the battery level becomes low.

---

*We recommend that you do not remove the battery when the phone is switched on as you may lose all your personal settings as a result. If you do remove it, the date and time settings are only memorized for a short while. As such, you need to reset the information after you have installed the battery back again.*

---

Once the battery and battery cover are installed, you can charge the phone. Plug in the connector as shown below. Then plug the other end into an AC power socket.



The battery symbol indicates the state of charge. During charging, the charge indicators will scroll; it takes around 4 hours to fully charge the battery. When all the scroll bars are steady, the battery is fully charged. You can then disconnect the charger. Depending on the network and condition of use, talk time and stand-by time can go up to 8.5 hours\* and 720 hours (1 months)\* respectively.

---

*\*Depending on the network conditions, user settings, method of use, etc the actual results may differ.*

---

*Keeping the charger plugged to the mobile phone when the battery is fully charged will not damage the battery. The only way to turn off*

*the charger is to unplug it, so it is advisable to use an easily accessible power socket.*

---

*If you do not intend to use your phone for several days, we recommend that you remove the battery.*

---


*You can use the phone while it is charging. If the battery is completely flat, the battery icon will only reappear after a few minutes of charging.*

---

## **Insert a micro SD card**

---

Gently slip the card into the micro SD card slot with the card's gold contacts facing downwards, then press it down until the card locks into place.



---

*To remove the micro SD card, push down the card into its slot and release it. The card will spring out of the slot.*

---

---

*The maximum capacity of micro-SD that X600 can support is up to 2GB.*

---

## **Setting hotkeys**

---

You can configure  $\uparrow$ ,  $\downarrow$ ,  $\leftarrow$ ,  $\rightarrow$ ,  $\square$  and  $\nabla$  to access your favorite features. Once they have been set, you can simply long press the keys to access the corresponding features.

Majority of the hotkeys have been preset and configured. To check the hotkey settings, go to [Settings](#) > [General](#) > [Shortcuts](#). To change the hotkey setting, press the numeric key you wish to change and Press  $\odot$  [Change](#), then select a feature to be associated with the numeric key from the following list:

- [Alarm](#)
- [Bluetooth](#)
- [Calculator](#)
- [Calendar](#)
- [View calls](#)
- [Camera](#)
- [Contacts](#)
- [Create message](#)
- [Firewall](#)
- [Flight mode](#)
- [Games](#)
- [Homepage](#)

- *Inbox*
- *Menu*
- *Meeting*
- *My files*
- *Ringtones*
- *Tasks*
- *Voice recorder*
- *Empty*
- *Languages*
- *Messages*
- *Music*
- *Profiles*
- *Shortcuts*
- *Unit converter*
- *Memo recorder*

***Numeric keys ,  and  have been preconfigured as the default keys to enter “+”, access voice mailbox and activate Meeting profile respectively, and cannot be modified.***

## 2. Calling

This chapter describes the features and options related to making and receiving calls.

### Switch on the phone

---

Long press  to switch on the phone.

You may set a security code (PIN code) on your phone to protect it from unauthorized use. When you have set a security code, you will be prompted to enter the corresponding security code when you switched on the phone.

1. Enter the PIN code. If you have entered the wrong number, press  *Clear* to clear it.
2. Press . The phone will validate the PIN code and commence network registration.
3. Once a network name is displayed on the screen, you are ready to make or answer a call. If there is no network name on the screen, you need to re-register.

---

*If you enter a wrong PIN code 3 times in succession, your SIM card will be blocked. To unblock it, you must request the PUK code from your operator. If you enter a wrong PUK code 10 times in succession, your SIM card will be permanently blocked and cannot be used*

*anymore. If this happens, please contact your network operator.*

---

### Switch off the phone

---

At all times, you can long press  to switch off the phone.

### Make a call

---

*You can make a call only when the network name appears on the screen.*

---

1. Enter the phone number.
2. Press  to dial the number or press  *Options* to enter options menu, then select *Dial*.

### IP Dial (If available)

When you select  *Options* > *Dial* > *IP dial* option, the mobile phone will automatically add the IP special service number preset by you in front of the phone number and then make the IP dial.

To set your desired IP number, go to *Calls* menu > *Call options* > *IP number*. See "Call options" on page 66.

### Make an international call

1. Long press  until "+" appears on the screen.
2. Enter the country code.

3. Enter the area code (normally without the 0 in front), followed by the phone number.
4. Press to call directly.

### **Make an emergency call**

You can make an emergency call anytime, irrespective of whether the mobile phone has been registered on the network.

1. In idle mode, enter the emergency call number (specific number in the caller's country)
2. Press .

**Note that an emergency call will not be stored in the call record.**

3. Alternatively, if there is no SIM card, pressing **SOS** can also bring you to the emergency call screen, displaying the call number. Then press or the **OK** softkey to directly make an emergency call and the dial animation will be displayed.

### **Speed dial**

You can set the numeric keys as speed dial keys. By long pressing the keys, you can make a call to certain contacts as defined.

To set your speed dial keys,

1. Go to **Settings > General > Speed dial**.

2. Select a numeric key that you wish to assign to a contact (2 to 9).
3. Press to select a contact from your phonebook. Press to confirm.

### **Answer and end a call**

When there is an incoming call, the number of the caller may be displayed if the caller has chosen to display his or her identity. If the number is stored in the phonebook, the corresponding name will be displayed instead of the number.

Answer the call: press / or open the phone if the **Active flip** option is **On** (see See "General" on page 70).

End the call: press or close the phone.

### **Options during a call**

During a call, you can press to activate/cancel **Handsfree** or press **Options** to carry out the following operations:

- Put the call on **Hold**
- **Mute/Unmute** the call
- **Record** phone conversation (which includes 3 sub-options: **Record both**, **Record opposite party** and **Record own**)
- Make a **New call**

- End the current call

### **Mute or unmute a call**

If you select **Mute**, the microphone will be deactivated.

When you switch from one call to another, muting will be cancelled.

### **Call recording**

During a call, press  **Options** and select **Record** to access the 3 recording options; namely, **Record both** (default), **Record the opposite party** and **Record own** (applicable to two-party calls or multi-party calls). When you end the call, the recording will stop and be saved automatically in AMR format under **My files** > (**Phone** or **Micro SD card**) > **Sounds**.

**There is no limit to the length of the recording; the recording will stop only when you press  key to stop the recording, when there is insufficient memory, or when the call has ended.**

### **Adjust speaker/earpiece volume**

During a call, call on hold or call waiting, you can press + / - side key to increase or decrease the volume (if you are not browsing the call options menu).

When the volume has been set, the call volume will take effect immediately and the settings will be applied to your subsequent calls.

## **Make a second call (Network dependent)**

---

You can make a second call by putting the current call on hold:

1. During a call with Party A, you can enter Party B's number using the keypad.
2. Press  to dial Party B's number. Party A will be put on hold automatically.

### **Switch calls (Network dependent)**

When you have one active call and one call on hold, you can press  **Swap** to switch between the 2 calls.

## **Make a Conference Call (Network dependent)**

---

Your phone supports multi-party call of up to five members.

When on the phone, you can carry out the following operations to establish the multi-party call:

1. Make a second call. The first call will be put on hold automatically.
2. Select *Conference Call* from the call menu. The two calls will be combined and a conference call is established.

During the multi-party call, you can answer a new incoming call or add a new member to the call by dialing the new member (the ongoing multi-party call will be put on hold automatically). Once the call is established, select *Establish conference call* from the call menu to add the new member to the multi-party call (you can add up to five members).

If you wish to separate one member from the call, you can select *Split conference call* during the multi-party call. To disconnect a member from the call, select *End call in conference*.

## Answer a second call (Network dependent)

---

If you have activated *Call waiting* (enabled by default on your phone), you will be alerted when there is a second incoming call. You can:

1. Press  to answer the second call. The current call will be put on hold automatically.

2. Press  to reject the second call and continue with your current call.
3. When there is one active call and one call on hold, you can press  *Swap* or  *Options* to carry out the following operations:

- *Conference call*
- *Call transfer*
- *Handsfree*
- *Mute*
- *Record*
- *End all calls*
- *End calls*
- *View contacts*
- *Menu*

---

*If you press the numeric keys, the notepad editor will be opened under call waiting mode.*

---

## Contact Picture

---

This feature allows you to link a contact in your phonebook to a photo you have taken using the camera function, or a picture you have downloaded via WAP or data cable. During a call, if the other party's name card is linked to a picture, the incoming call background will display the corresponding picture. This feature is referred to as *Contact picture*.

---

*Contact picture shall be a photo or picture on the phone memory. The photo size should not be larger than 176 x 220 pixels.*

---

### 3. Text and number entry

#### Input method

Your mobile phone supports several input methods, which include:

- T9 Pinyin: Enter chinese characters with T9 Pinyin;
- T9 Stroke: Enter Chinese characters with T9 wubi and stroke components;
- T9 Traditional Chinese stroke: Enter Traditional Chinese characters with Wubi or stroke components;
- T9 English (T9eng/T9Eng): Enter English text using T9 English;
- T9 input: Enter text using T9 input;
- Multi-Tap (Abc/abc/ABC): Press the keys that are marked with the corresponding letter you wish to enter. Press once to get the first letter on the key, press twice quickly to get the second letter and so on until the letter you want is displayed on the screen.
- 123: Enter numbers

This phone supports T9 Simplified Chinese association input method as well.

*Depending on the language you select for your phone, the supported input methods may vary.*

\*During text editing, you can press  to switch input mode; the status bar on the screen will display your current input mode.   represents Simplified Chinese Pinyin input mode;  represents Simplified/Traditional Chinese stroke input mode; 『Abc』, 『abc』, 『ABC』 represents English alphabets input mode; 『123』 represents numeric input mode. In addition, you can press  to input punctuations.

The text editor remembers the last input method you have used before you exit the editing screen. When you access the editor again, it will automatically select the last input method you have used.

#### T9<sup>®</sup> input



Tegic Euro. Pat.  
App. 0842463

T9<sup>®</sup> predictive text input is an intelligent editing mode for messages, which includes a comprehensive dictionary. It allows you to quickly enter text. You need to press only once on the key corresponding to each letter needed to spell a word: keystrokes

input are analyzed and the word suggested by T9® is displayed at the pop-up window. If there are more than 3 candidates, a scroll bar is shown, press + or - to browse the list and choose from those proposed by the T9® built-in dictionary (see example below). After you have input the word, press ⊖ or ☐ to confirm.

### How to use it?

Alphabets and symbols represented by each key are as follows:

- ⓪ to Ⓠ To input letters.
- ▲ or ▼ To browse the last or next candidate word.
- ⊖ *Select* To confirm the letter or word.
- ☐ *Clear* Short press to clear a letter, long press to clear all entries.
- ⇧ Shift case, select input mode. Long press to turn on/off T9 feature.
- Ⓢ Short press to activate/deactivate punctuation mode, long press to select input language.

### Example: How to enter the word "Home"

1. Press ⓪ Ⓛ Ⓢ Ⓦ Ⓜ, the screen displays the first word on the list: *Good*.
2. Press ▼ to browse and select *Home*.
3. Press ☐ *Select* to confirm *Home*.

### Basic text input

If you wish to use basic text input mode, press Ⓢ to select "ABC", "Abc" or "abc" basic text input. This method requires multiple key presses to reach the desired character: the letter "h" is the second letter on the ⓪ key, so you must press ⓪ twice to enter "h". Using this mode requires you to press a key as many times as is equal to the order of the letter.

To enter the word «Home» in basic text input mode, you should therefore key ⓪, ⓪ (*GH*) Ⓠ, Ⓠ, Ⓠ (*MNO*), Ⓠ, Ⓠ (*MNO*), Ⓜ, Ⓜ (*DEF*).

Letters, numbers and symbols are located on each key as follows:

#### Key

#### Letters and numbers

Ⓛ

Space | @ \_ # = < > ( ) & £ \$ ¥

Ⓜ

a b c 2 à ä å æ ç

	d e f 3 é è D F
	g h i 4 G ì
	j k l 5 L
	m n o 6 ñ ò ö ø
	p q r s 7 b P Q S
	t u v 8 ü ù
	w x y z 9 W X Y
	Input space
	Switch text input mode
	Input symbol

## Pinyin Input

Press  and select Pinyin input mode. Each Pinyin letter is represented by one of the numeric keys as shown below: (Note that Pinyin input mode is solely meant for the input of Simplified Chinese characters. You cannot input Traditional Chinese characters).

	 ABC	 DEF
	 JKL	 MNO
	 TUV	 WXYZ
	Mode  	 Punctuation

The general steps of using Pinyin input method are as follows:

1. Enter Pinyin letters  to   
 to clear
2. Select Pinyin combination ◀ or ▶
3. Confirm Pinyin combination 
4. Select from candidate list ◀ or ▶ / ▲ or ▼  
(scroll list)
5. Confirm selection 
6. Select and enter association character, or return to step 1 to enter new words.
7. Or press  to exit from association character input mode, then press  to complete the editing.

Enter the pinyin letters accordingly. Press once on the key corresponding to the pinyin letter without having to consider its position on the key. Pinyin input method will automatically select and list all possible combinations for you to select.

For example, to input the character [王], with the Pinyin letters [wang], press     and use ▶ to select the desired pinyin combination for [wang], then press  to confirm combination.

As soon as you have selected and entered a character, the candidate list will be updated and a list of association characters will be displayed. Press ◀ or ▶ to select the desired association character and press  to confirm entry. This speeds up the input process further.

When you have finished editing a name on the phonebook or SMS, press  to exit from association character input mode and press  to confirm completion of the editing process.

## Stroke input

Press  to select stroke input mode. The strokes are represented on each key as follows:

1. — Horizontal	2.   Vertical	3. / Left-falling
4. \ Right-falling	5. ⇨ Over-down	6. ? Special
7.	8.	9.
Mode T9 ↗	0.	⌂ Punctuation

The basic steps of Stroke input are as follows:

1. Enter strokes 1 to 5 (excluding 7 and 9) ⌂ to clear.
2. Select from candidate list ◀ or ▶ / ▲ or ▼ (scroll list)
3. Confirm selection ⊙
4. Select and enter association character, or return to step 1 to enter new strokes.
5. Or press ⌂ to exit from association character input mode, then press ⊙ to complete the editing.

The principle of stroke input is to dissect and separate every stroke of a chinese character according to sequence. When you wish to input the character, press the keys corresponding to the required strokes according to sequence to get the

desired character. The stroke input method in this phone classifies a chinese character into 5 basic strokes: (horizontal, vertical, left falling stroke, right falling stroke and over-down) as well as a special stroke. When the stroke you need does not correspond to the 5 basic strokes, replace it with the special stroke.

The examples below will give you a clearer understanding of how to use stroke input method:

1. 木:  - +  | +  / +  \
2. 田:  | +  ↗ +  - +  | +  -  
+  ▶
3. 加:  ? +  / +  | +  ↗ +  -
4. 凉:  \ +  ? +  \ +  - +  | +  
 | ↗ +  - +  ? +  / +  \
5. 陈:  ? +  | +  - +  ? +  ? +  
 / +  \

Generally, you will be able to find a desired character before you finished entering all the strokes. After you have entered the name of the phonebook or SMS, press  to exit from the association character list and press  to confirm completion of text editing.

---

*The input mode for Traditional chinese stroke and Simplified Chinese stroke are similar, with the exception of the character coding.*

---

## 4. Entertainment



This section describes the games and additional tools installed on your mobile phone.

---

*Some of the features described here are dependent on the configuration of your mobile phone, the country in which you purchased your mobile phone, and/or your service provider.*

---

### Games

---

#### **Default games**

This menu features games that are pre-installed in your mobile phone. Press  to enter the main menu from idle mode and select [Entertainment](#) > [Games](#).

### Java

---

Your mobile phone features a Java run-time environment, which allows you to run Java applications, such as games downloaded from the network. You can also download games and other

applications via WAP or USB and run them in the Java environment.

When installing games via a USB data cable, make sure that the application files are under the same file folder as the .jar and .jad files.

## 5. Browser



Your phone comes with a WAP browser. You can obtain news, sports and weather information, as well as services from the internet via the WAP browser.

---

*This feature is available only if your subscription includes WAP access services. The settings have been pre-configured (depends on country variants) and you do not need to modify them. For more information, please contact your network operator.*

---

### WAP

---

*Normally, the phone would have been pre-configured. If you wish to add or modify the configuration parameters, you need to obtain the necessary information from your network operator before you proceed. Philips is not liable to give prior notification nor shall it bear any consequences for any failures arising from*

*changes of configuration made by you or by the network operator. Please check with your network operator for the most updated information.*

---

### Homepage

Select this menu to access the homepage directly. You can also set the homepage address in the settings menu.

### Bookmarks

You can save the current web page or the web pages that you frequently visit to the *Bookmarks* list, manage and organize them.

When you enter the menu, a list of bookmark entries is displayed. To connect to the web address of a particular bookmark entry, select an entry using  $\blacktriangle$  or  $\blacktriangledown$  and press  $\ominus$ .

If there are no existing entries, you can select the following options to add and manage your bookmarks:

To add a new bookmark:

Go to *Bookmark* menu    Press  $\ominus$  to enter the main menu from idle mode    and select *Browser > Bookmarks*.

Select [Add Bookmark](#)

Add a new bookmark

Press  $\ominus$ .

Enter the [Title](#) and [URL](#) of the new bookmark and press  $\ominus$  [Save](#).

To edit a bookmark:

Go to [Bookmark](#) menu

Press  $\ominus$  to enter the main menu from idle mode and select [Browser](#) > [Bookmarks](#).

Select a bookmark you wish to edit

Press  $\blacktriangle$  or  $\blacktriangledown$  and press  $\square$  [Options](#). Then select [Edit](#) and press  $\ominus$  [Select](#).

Edit the bookmark

Edit the [Title](#) and [URL](#) of the bookmark and press  $\ominus$ .

### **Enter address**

Enter the web address and press  $\ominus$  to connect, press  $\square$  [Back](#) to return to previous web page.

### **History**

This menu allows you to quickly access the last web page you have visited.

1. When you enter this menu, the web pages you have previously visited will be listed.

2. Select a web page on the list and press  $\ominus$ . Then press  $\square$  [Options](#) to access the following:

[Open](#)

[Info](#)

[Navigate](#)

[Exit](#)

[Go to](#)

[History](#)

[Save as](#)

[Send as SMS](#)

### **Settings**

This menu allows you to configure the web settings for web browsing. Your phone may have been pre-configured with the settings of a specific network operator. If you are a subscriber of the network operator, you may start using your WAP browser immediately. Otherwise, you need to re-configure the settings.

---

*Philips is not liable to give prior notification nor shall it bear any consequences for failures arising from changes in configuration made by you or by the network operator, or changes in WAP address or contents made by the internet content provider. Please check with your*

## ***network operator and your internet content provider for the most updated information.***

---

The following options are available:

- WAP profiles* Allows you to configure the *WAP profiles*.
- Clear cache* Allows you to set the *Clear cache*.
- Clear history* Allows you to remove the web history.
- Options* Allows you to *Show images*, *Exit info* or *Enable cookies*.

## **Push Inbox**

---

Allows you to check your Push messages and configure your Push settings, such as select whether or not to accept Push messages, delete push messages, etc.

## 6. Media player



### Music Player

---

This feature allows you to download music from the network, save the audio files, edit your playlist, and play music. The phone supports audio files in MP3, AAC, AAC+, and WMA formats. However, only MP3 format is supported with the bluetooth headset.

#### Tracks

This feature allows you to play downloaded music in your *Phone* memory or *Micro SD card* (under *Sounds* folder). From the listed tracks, use  $\blacktriangle/\blacktriangleright$  to select the music file you want to play and then press  $\ominus$  *Open* to open the music player to play the selected track or press  $\square$  *Options*.

#### Options

*Add to playlist*

*Delete track*

#### Description

Open the playlist, select a playlist and add the selected track to the playlist.

Delete the selected track.

#### Details

View detailed information of the selected track.

#### Playlists

You can create up to 10 playlist. To create a new playlist, select *New playlist*. Enter the playlist name and press  $\ominus$ . Then use  $\blacktriangle/\blacktriangleright$  to select a playlist, press  $\ominus$ . Press  $\ominus$  and select the tracks that you want to add to the playlist. Then press  $\ominus$  *Done* to confirm and store the songs in the playlist.

In the playlist, press  $\ominus$  *Open* to play the selected track or press  $\square$  *Options*.

#### Options

*Edit playlist*

*Rename playlist*

*Delete playlist*

#### Description

Select or deselect a track to add or delete it.

Modify the playlist name.

Delete the current playlist.

### Tracks sequence

Modify the play sequence of the current playlist. Use  $\blacktriangleleft/\blacktriangleright$  to select the track you want to move. Press  $\ominus$  **Select**. Use  $\blacktriangleleft/\blacktriangleright$  to move the track to the desired position. Press  $\ominus$  **Insert**.

### Details

View detailed information of the selected file.

### Artists

A list of singer names is displayed on the screen. You can press  $\blacktriangleleft/\blacktriangleright$  to select a certain artist and press  $\ominus$  to display all tracks of the selected artist.

From the listed tracks, use  $\blacktriangleleft/\blacktriangleright$  to select the music file you want to play. You can press  $\ominus$  **Open** to open the music player to play the selected track or press  $\square$  **Options**.

#### Options

#### Description

##### Add to playlist

Open the playlist, select a playlist and add the selected track to the playlist.

##### Delete track

Delete the selected track.

##### Delete artist

Delete all tracks of the same artist.

### Details

View detailed information of the selected track.

### Last played

List the last 10 tracks you have played, and the last played track is displayed at the top of the list.

### Settings

The available options include:

#### Options

#### Description

##### Play in background

Allows you to listen to the music when you exit the music player application. You can select **Ask first**, **Always** or **Never**.

##### Play mode

Select between **Repeat one**, **Repeat all**, **Shuffle and repeat**, **Shuffle** or **Off**.

##### Help

Display descriptions on how to use the music player.

##### Refresh all lists

All tracks stored in the phone memory and the memory card will be refreshed.

## Now playing

The screen displays the last played song. This function enables you to go on playing the last playlist you were listening to.

## Keys operation

The keypad operations during music playback are as follows:

Key	Operation
⏸ key	Short press to Start/Pause/resume music playback.
◀ or ▶	Short press to select the previous song/next song. Long press to fast rewind/fast forward the track during playback.
+ or -	Adjust volume. Once you have set the volume, the settings will be saved until the next time you adjust it again.
☰ <i>Options</i>	Open options menu.
☐ <i>Back</i>	Return to previous menu. When you exit the music player, the music playback will stop.

Press ☰ *Options* to carry out the following operations:

### Options

*Play in background*

*Add to playlist*

*Play mode*

*Off*

*Details*

### Description

Allows you to listen to the music when you exit the music player application. You can select *Ask first*, *Always* or *Never*.

Open the playlist, select a playlist and add the selected track to the playlist.

Select between *Repeat one*, *Repeat all*, *Shuffle and repeat*, *Shuffle* or *Off*.

Turn off the music player.

View detailed information of the selected file.

## 7. Camera



### Camera

---

Your mobile phone features a 2.0 mega pixel digital camera that allows you to take pictures and record videos, store them in your phone and memory card, use them as wallpaper or send them to your friends.

*Please ensure that the camera lens is clean before you take pictures, as small dust particles can strongly affect the picture quality.*

---

#### Camera mode

Consult the table below on how to carry out some common operations with your camera.

#### How to ...

Launch Camera	Press $\odot$ to enter the main menu from idle mode and select <i>Camera</i> .
Switch between Camera and Video recorder	Press $\blacktriangleleft/\blacktriangleright$ .

Zoom in/out

Press  $\blacktriangleleft/\blacktriangleright$ .

*Only available for picture resolution of 640\*480 or below.*

---

Adjust brightness

Press  $+/-$  side keys.

*Brightness level is -3 to +3. Default level is 0.*

---

Take a picture

Press  $\odot$ .

*The picture will be automatically saved and stored in My files > Pictures.*

---

Exit from Camera and return to the idle mode

Press  $\square$  key or  $\square$  *Back* twice.

At any point in time, you can press  $\square$  key to cancel the current operation and return to idle mode.

#### Camera option menu

When the camera mode is activated and before a picture is taken, you can change a number of settings by pressing  $\square$  *Options*.

**Options**      **Description**

*Picture resolution*      Select image size: *1600\*1200, 1280\*1024, 1024\*768, 640\*480 and 176\*220.*

*Picture Quality*      Select image quality: *Super fine, Fine and Normal.*

---

*The last selected value will remain active until you change it again.*

---

*View picture*      Enter *My files > (Phone or Micro SD card) > Pictures* to view the pictures taken. You can also access *View pictures* and press  *Open* to view the picture taken directly.

---

*You may save to the Micro SD card a photo greater than 500K in size. To view such a photo, select it, and copy it to your phone memory first (press  Options > Advanced > Copy to copy the photo; enter My files > Phone > Pictures, select a location, and press  Options > Advanced > Paste here).*

---

*Camera Mode*      *Color effects: Off (default), B&W, Sepia, Blue, Red or Emboss.*

---

*The selected color effect will be displayed on the screen in real time.*

---

*Night mode: On or Off*  
*Self-timer: On or Off*

---

*The time limit is 8 seconds.*

---

*Multishot: On or Off*

---

*Three pictures can be taken at the same time.*

---

*Advanced*      *Storage location: My files or Memory card*

*Default name:* modify the default name of the photo

*Frequency: 50HZ or 60HZ*

*Full screen preview: On or Off*

### **Photo preview option menu**

Once you have activated the camera, simply press  to take a picture. The picture is automatically saved and displayed on the screen. You can press 

to *Send* the picture *via Bluetooth* or *via MMS*, or  *Options* to carry out the following operations:

<b>Options</b>	<b>Description</b>
<i>Delete</i>	Delete the current picture.
<i>Rename</i>	Change the name of the picture.
<i>Capture</i>	Return to the viewfinder screen to take a new picture.
<i>Set as contact picture</i>	Link the picture to a contact in your mobile phone so that the picture will be displayed when the contact calls you.
<hr/> <b>Available for picture resolution of 176*220 only.</b> <hr/>	
<i>Edit</i>	Modify or edit the selected picture. Press $\blacktriangleleft/\blacktriangleright$ and $\ominus$ to select your edit options.
<i>Set as wallpaper</i>	Set the picture as a wallpaper in idle screen.
<i>Details</i>	View detailed information of the picture.

---

**When there is not enough memory space, you will not be able to save the picture and you will**

***be prompted with a warning message. You have to delete existing pictures before you can store new ones.***

---

## **Video recorder**

---

This option allows you to record short videos. You can play the video, store it in your phone or in the memory card. You can also send the video to your friends via MMS or Bluetooth.

### **How to ...**

Launch Video recorder      Press  $\ominus$  to enter the main menu in idle mode and select *Camera*. Press  $\blacktriangleleft/\blacktriangleright$  if necessary.

Switch between Camera and Video recorder      Press  $\blacktriangleleft/\blacktriangleright$ .

Adjust brightness      Press  $+/-$  side keys.

---

***Brightness level is -3 to +3. Default level is 0.***

---

Record a video

Press **⏻** key once. Press again to stop recording.

---

*The video will be automatically saved and stored in My Files > Videos.*

---

Exit from Video mode and return to idle mode

Press **⏻** key or **⏪** *Back* twice.

### Video option menu

When the video mode is activated and before you start recording, you can change a number of settings by pressing **⏻** *Options*.

#### Options

#### Description

*Video quality*

Select video quality: *Fine* or *Normal*.

---

*The last selected value will remain active until you change it again.*

---

*View video*

Enter *My Files* > (*Phone* or *Micro SD card*) > *Videos* to view the recorded videos. You can also access *View video* and press **⏻** *Play* to view the recorded videos directly.

*DV mode*

*Color effect: Off* (default), *B & W*, *Sepia*, *Blue*, or *Red*

---

*The selected color effect will be displayed on the screen.*

---

*Video format: MPEG-4* or *H263*

*FPS: 5, 10* or *15* frame per second.

*Advanced*

*Storage location: My files* or *Memory card*.

*Default name:* modify the default name of the video

*Mute: On* or *Off*

---

*If you select On, sound will not be recorded.*

---

Video length: *MMS* (default) or *Unlimited*.

---

*If you select MMS, the size of the recorded video will be smaller than the currently specified maximum MMS size. Recording will stop when reaching the maximum MMS size and the video will be stored automatically. If you select Unlimited, there will be no restrictions on the size of the recorded video. The maximum size shall be determined by the memory capacity of your mobile phone or the memory card.*

---

## Video Playback

Once you have activated the video mode, simply press  to start recording. Press again to stop recording. The video is automatically saved and the last recorded scene is displayed on the screen. You can press  *Play/Pause* to play the recorded video

or pause the playback, or press  *Options* to carry out the following operations:

Options	Description
<i>Send</i>	Send the recorded video: <i>Via Bluetooth</i> and <i>Via MMS</i> .
<i>Delete</i>	Delete the recorded video.
<i>Record new</i>	Return to video mode to record a new video clip.
<i>Details</i>	View detailed information of the recorded video.

---

*When there is not enough memory space, you will not be able to save the recorded video and you will be prompted with a warning message.*

---

## 8. Messages



### Create message

---

#### SMS

SMS enables you to send text messages to the other party, which is a convenient and affordable mode of communication. You can use the *SMS* menu to send messages to another handphone or a device that is capable of receiving SMS.

Your phone can store up to 1000 messages. Once you have reached 1000 messages, the screen will flash an icon to alert you. You need to delete some messages in order to receive new ones.

#### Create, edit and send SMS

*You need to enter the correct message centre number before you can send SMS. The number can be obtained from your network operator.*

1. In idle mode, press  $\odot$  to enter the main menu.
2. Select *Messages* > *Create Message* > *SMS* and press  $\odot$ . The SMS editing screen will appear.

3. Enter the SMS content in the SMS editor and press  $\square$  *Options* to carry out the following operations:

<i>Clear text</i>	Delete the text on the editing screen.
<i>Save</i>	<i>Save as draft</i> : save the SMS as draft. <i>Save as template</i> : save the SMS as template.
<i>Insert contact</i>	Insert the contact from the phonebook list.
<i>Use template</i>	Insert a preset message.
<i>Exit editor</i>	Exit from the SMS editor.
<i>Spell word</i>	Select Chinese pinyin input method.
<i>Help</i>	Displays the shortcuts for editing.

---

*If your SMS is not sent successfully, you can resend it. If your SMS cannot be sent successfully after several attempts, please check if your SMS center number has been set correctly.*

---

*When editing SMS, for certain reasons (such as an incoming call, out of battery), you are forced*

to exit from the SMS editing screen before you managed to send or save your message successfully, the edited message will be saved automatically. The next time you enter the SMS editor, the message will be displayed on the screen.

---

### **MMS (network dependent)**

Your phone allows you to send and receive multimedia messages, known as MMS, which features texts, pictures, sound and video clips. MMS can comprise one or several slides. Whether you send it to an e-mail address or to another mobile phone, the MMS will be played as a slide show. Your phone can support 50 MMS (maximum 100KB).

*Before you can send MMS, you need to enter the correct MMS Center number and ensure that the network profile of your MMS has been correctly configured. You can obtain such information from your network operator.*

---

### **Create, edit and send MMS**

1. In idle mode, press  $\odot$  to enter the main menu.
2. Select *Messages > Create Message > MMS* and press  $\odot$ . The MMS editing screen will appear.

3. Enter the MMS content in the MMS editor and press  $\odot$ . Then press  $\square$  *Options* to carry out the following operations:

*Insert object*      Insert picture, video, melody, page or object.

*Only a picture, a melody and a video can be inserted on one page. If 3 of them exist at the same time, only one can be saved.*

---

*Edit subject*      Edit the subject of the MMS

*Preview*              Preview the current MMS.

*Page timing*        Set play time of the MMS slides. The default value is 30 seconds.

*Save*                    *Save as draft*: save the MMS as draft.  
*Save as template*: save the MMS as template.

*Exit editor*            Exit from the MMS editor.

*Spell word*            Select Chinese pinyin input method.

*Help*                    Displays the shortcuts for editing.

When there is more than one page, you can press  $\leftarrow$  /  $\rightarrow$  to view the different pages of the MMS. At the same time, the title bar at the top of the screen will

display the current page you are viewing and the total number of pages in your MMS.

4. Press [Send](#) to access the next option menu:

[Contacts](#) Select the contact from the [Contacts](#) list.

[Groups](#) Select the group from the [Groups](#) list.

[Phone number](#) Enter the phone number of the recipient.

[Recently list](#) Select from the list of recipients you received the messages from.

[Email address](#) Enter the e-mail address of the recipient.

## **Inbox**

---

The Inbox stores the messages you have received.

1. In idle mode, press [Inbox](#).

If there are messages in the [Inbox](#), they will be listed on the screen in the order they were received (the most recent message will appear at the top of the list).

2. Press to select a message. When a message is selected, its contents will be displayed on the screen. Press [View](#) to view

the selected messages or press [Options](#) to carry out the following operations:

### [Reply](#)

The sender's number will be used as the destination number automatically and the message editor will be activated. Enter your reply and send the message.

### [Forward](#)

When you select [Forward](#), the contents of the selected message will appear in the message editor. You may edit the message before sending.

### [Delete](#)

Delete the message from the [Inbox](#).

### [Add to blacklist](#)

(if applicable)

When you add the contact to the blacklist, you will not receive call/message from this contact anymore.

### [Archive to SIM](#)

(if applicable)

Move the selected message to the SIM card.

### [Move to my favourite](#)

Move the selected message to [My Favourites](#).

*Details* View information of the message such as date, time and sender.

*Dial* Extract the sender's number from the message and dial the number.

*Smart Search* Search the messages by sender's name, number or time.

*Select multiple* You can choose to *Select one by one* or *Select all*. You can press  to *Select/Undone* the operations on multiple messages. Checkboxes will be marked on the left of the selected message. Press  *Options* to delete the selected messages, or you can move them to My favourites.

3. Press  to enter the next screen whereby the message details will be displayed. Press  *Reply* the message by *SMS* or *MMS* or press

 *Options* to carry out the following operations:

*Forward* When you select *Forward*, the contents of the selected message will appear in the message editor. You may edit the message before sending.

*Delete* Delete the message from the *Inbox*.

*Extract numbers* Opens the list of numbers available in the message. In this list, the  option opens a pop-up window showing the following options:

- *Save*
- *Update existing*
- *Dial*
- *Send message*

*Add to blacklist* When you add the contact to the blacklist, you will not receive call/message from this contact anymore.

*Move to my favourite* Move the selected message to *My Favourites*.

<i>Move to spam box</i>	Move the selected message to <i>spam box</i> .
<i>Details</i>	View information of the message such as date, time and sender.
<i>Dial</i>	Extract the sender's number from the message and dial the number.

## Sent

The *Sent* box allows you to save the messages you have sent successfully.

1. In idle mode, press  $\ominus$  to enter the main menu.
2. Select *Messages* > *Sent* and press  $\ominus$ .  
If there are messages in the *Sent* box, they will be listed on the screen.
3. Press  $\leftarrow/\rightarrow$  to select a message. When a message is selected, its contents will be displayed on the screen. Press  $\ominus$  *View* to view the selected

message, or press  $\square$  *Options* to carry out the following operations:

<i>Resend</i>	Resend the message to the recipient.
<i>Forward</i>	When you select <i>Forward</i> , the contents of the selected message will appear on the message editor. You may edit the message before sending.
<i>Delete</i>	Delete the message from the <i>Sent</i> box.
<i>Archive to SIM</i> (if applicable)	Move the selected message to the SIM card.
<i>Move to my favourites</i>	Move the selected message to <i>My Favourites</i> .

**Details** View information of the message such as date and time.

**Select multiple** You can choose to *Select one by one* or *Select all*. You can press  $\ominus$  to *Select/Undone* the operations on multiple messages. Checkboxes will be marked on the left of the selected message. Press  $\square$  *Options* to delete the selected messages, or you can move them to My favourites.

4. Press  $\ominus$  to enter the next screen whereby the message details will be displayed. Press  $\ominus$  *Resend* to resend the selected message, or press  $\square$  *Options* to carry out the following operations.

**Forward** When you select *Forward*, the contents of the selected message will appear on the message editor. You may edit the message before sending.

**Delete** Delete the message from the *Outbox*.

**Archive to SIM** (if applicable)

)

**Move to my favourites** Move the selected message to *My Favourites*.

**Details** View information of the message such as date and time.

## Outbox

---

The *Outbox* allows you to save the messages you have not sent successfully.

1. In idle mode, press  $\ominus$  to enter the main menu.
2. Select *Messages > Outbox* and press  $\ominus$ .  
If there are messages in the *Outbox*, they will be listed on the screen.
3. Press  $\blacktriangleleft/\blacktriangleright$  to select a message. When a message is selected, its contents will be displayed on the screen. Press  $\ominus$  *View* to view the selected message, or press  $\square$  *Options* to carry out the following operations:

**Resend** Resend the message to the recipient.

**Forward** When you select *Forward*, the contents of the selected message will appear on the message editor. You may edit the message before sending.

*Delete* Delete the message from the *Sent* box.

*Move to my favourites* Move the selected message to *My Favourites*.

*Details* View information of the message such as date and time.

*Select multiple* You can choose to *Select one by one* or *Select all*. You can press  $\ominus$  to *Select/Undone* the operations on multiple messages. Checkboxes will be marked on the left of the selected message. Press  $\square$  *Options* to delete the selected messages, or you can move them to My favourites.

4. Press  $\ominus$  to enter the next screen whereby the message details will be displayed. Press  $\ominus$  *Forward* to forward the selected message or press  $\square$  *Options* to carry out the following operations.

*Resend* Resend the message to the recipient.

*Delete* Delete the message from the *Outbox*.

*Move to my favourites* Move the selected message to *My Favourites*.

*Details* View information of the message such as date and time.

## Drafts

---

List the messages that were created and saved but were not sent, and messages that were automatically saved before you were able to save or send them when you exit from the message editor.

Select a message from the Draft box and press  $\ominus$  *View* or press  $\square$  *Options* to: *Send, Edit, Delete, Details, Select multiple*. If you select *View*, the subsequent procedures would be similar to the Inbox operations.

## My favourites

---

This menu contains all the messages received and saved in the phone memory via *Move to my favourite* option.

1. In idle mode, press  $\ominus$  to enter the main menu.
2. Select *Messages > My favourites* and press  $\ominus$ . If there are messages in *My favourites*, they will be listed on the screen.
3. Press  $\blacktriangle/\blacktriangledown$  to select a message. When a message is selected, its content will be displayed on the

screen. Press  **View** to view the selected messages or press  **Options** to carry out the following operations:

- Details** View the information of the message such as date, time and sender.
- Reply** The sender's number will be used as the destination number automatically and the message editor will be activated. Enter your reply and send the message.
- Forward** When you select **Forward**, the contents of the selected message will appear in the message editor. You may edit the message before sending.
- Delete** Delete the message from **My Favourites**.
- Restore location** Move the message to the original location where the message is sent or received.
- Dial** Extract the sender's number from the message and dial the number.

#### Select multiple

You can choose to **Select one by one** or **Select all**. You can press  to **Select/Undone** the operations on multiple messages. Checkboxes will be marked on the left of the selected message. Press  **Options** to delete the selected messages, or you can move them to My favourites.

4. Press  to enter the next screen whereby the details will be displayed. Press  **Options** to carry out the following operations:

- Details** View information of the message such as date, time and sender.
- Reply** The sender's number will be used as the destination number automatically and the message editor will be activated. Enter your reply and send the message.
- Forward** When you select **Forward**, the contents of the selected message will appear in the message editor. You may edit the message before sending.
- Delete** Delete the message from **My Favourites**.

*Restore location* Move the message to the original location where the message is sent or received.

*Dial* Extract the sender's number from the message and dial the number.

## Spam box

---

This menu allows you to filter messages after the firewall has been set. When the firewall is activated, any message from a person on your blacklist will go to the spam SMS box automatically.

## SIM archive

---

In the menu, you can see the read and unread messages saved in the SIM Card. Press  *View* to view the selected messages or press  *Options* to carry out the following operations:

Options	Description
<i>Reply</i>	Reply the message.
<i>Forward</i>	Forward the message to other recipients.
<i>Delete</i>	Delete the message.

*Add to blacklist* When you add the contact to the blacklist, you will not receive call/message from this contact anymore.

*Move to my favourite* Move the selected message to *My favourites*.

*Details* View information of the message, such as date, time and sender, etc.

*Dial* Call the sender of the message.

*Select multiple* You can press  to select/cancel the operations on multiple messages. Checkboxes will be marked on the left of the selected message. You can delete the selected messages.

## Templates

---

This menu allows you to select a message saved as a SMS or MMS template. You can create, send, modify and delete your preset messages.

## E-mail

---

Your phone can send and receive e-mail messages, provided this service is included in your subscription. You must already have an e-mail account and have received the settings from your

email service provider. In some cases, your mobile phone service provider may also provide an e-mail service.

### Create e-mail

To write an e-mail, select *Email > Create*. Enter the address (*To*), a copy (*Cc*), or blind copy (*Bcc*), *Subject* and the e-mail *Content*. When you have finished writing your e-mail, press  to access the following:

- Save* Save the message in the draft box without sending it.
- Send* Send the e-mail.

### Inbox

This menu allows you to connect to your mailbox and download the e-mail headers. Press  to *Receive* the e-mails. You may then select an e-mail header and press  to access the following options: *View*, *Delete*, *Reply*, *Reply all*, *Forward*, *Delete all*, *Receive*.

### Drafts

The menu lists all the e-mails you have saved but not sent. Press  to: *Edit*, *View*, *Delete*, *Delete all*.

### Outbox

The menu lists all the e-mails you have sent. Press  to: *Edit*, *View*, *Delete*, *Delete all*.

### Check mail

The menu allows you to connect to your mailbox and to download the e-mails. This might bring up a message requesting airtime. Select *Yes* to continue and receive new e-mails.

### Settings

This menu allows you to edit e-mail's *Account Settings* or *Activate* one of the available profiles by pressing . Use *\*/\** key to access the menu list, press  or numeric keypad to edit the content. In the editing screen, press  to return, press  to *Save* and  to *Clear*. You may edit the following details:

Menu	Description
<i>Profile name</i>	To name the profile.
<i>E-mail address</i>	To enter an e-mail address.
<i>User ID</i>	To enter a login name.
<i>Password</i>	To enter the password.

<i>Number of mails received at a time</i>	To define the number of mails received at a time.
<i>Incoming server</i>	To set the POP information used to receive e-mails.
<i>Outgoing server</i>	To set the SMTP information used to send e-mails.
<i>SMTP authentication</i>	To turn on/off the authentication.
<i>Type</i>	To select POP3 or IMAP.

### **Exit**

You will be exited from the e-mail menu.

## **Advanced**

---

### **Cell Info**

This is a network service which allows you to receive text messages of various contents, such as news, traffic, etc. These messages are provided by the network to the subscribers within a certain network area. If this service is available, the network will provide you with the broadcast

channel numbers. It gives you access to the options listed below.

Options	Description
<i>Reception</i>	Select to turn on/off the reception of new cell broadcast messages.
<i>Topics</i>	Add, change or delete channels. <i>&lt;Add new&gt;</i> : Press  <i>Add</i> to add a new channel. <i>Change</i> : Edit a channel number. <i>Delete</i> : Delete a channel in the channel list.

### **Memory status**

This feature allows you to see how much memory space remains for messages in your phone and SIM card.

### **SMS timer**

You may set a specific time to send an edited text message to a particular contact.

This menu allows you to select *Add* to send text messages at specific times and display such messages in a list on the screen.

Select *Add* to enter into the SMS editing screen. Press  to open the contacts list and select a contact, or enter the phone number directly and

set message sending options. You can set the date and time to send the message.

When you select a message from the list of text messages configured for sending at specific times, you can press  [View](#) to view the details of the message or press  [Options](#) to carry out the following operations:

[Delete](#) Delete the message.

[Delete all](#) Delete all messages.

When you enter a message detail screen, you can press  [Send](#) to send the message to the recipient directly or press  [Option](#) to carry out the following operations:

[Edit](#) You can edit the contents, contact or date.

[Delete](#) Delete the message.

## Voice mail

---

This menu allows you to set your voice mailbox number and listen to voice messages your correspondents have left for you.

[You can forward your calls to your voice mailbox \(the phone number for callers to leave a message\) via the \*Call forwarding\* feature.](#)

---

## Call voice mail

When you receive a voice mail, the phone will send you an alert. You can then call your voice mailbox number to retrieve your voice mail.

In idle mode, long press  to call your voice mailbox directly. If the number is empty, you will be prompted to enter the number.

### Voice mail number

Generally, you can obtain two sets of numbers from your network provider:

- number for the caller to leave a message (this number can also be used for Call Forwarding)
- number for you to retrieve your voice messages

## Settings

---

### SMS

Select [Messages](#) > [Settings](#) > [SMS](#) to open the list of SMS accounts. Press  [Reset](#) to edit the SMS settings:

### Service center number

This menu allows you to save and edit the SMS service center number of your home network. If the service center number is empty, you will not be able to send any SMS.

## Validity period

Allows you to select the duration by which your messages will be stored in the service center. You can select from: *1 hour*, *12 hours*, *1 day*, *1 week* and *Maximum* (default). Press  $\swarrow/\searrow$  to select a value.

This option is useful when your recipient is not connected to the network and is not able to receive your messages immediately.

---

*This feature is subscription dependent.*

---

## Delivery report

You can select  $\odot$  to set this option *On* or *Off*. This option allows you to set whether or not to notify you the send status of your messages: successfully sent to the recipient, or not sent successfully.

---

*This feature is subscription dependent.*

---

## Signature

You can select  $\odot$  to set this option *On* or *Off* (Default is *Off*). If set to *On*, it opens an editor where you can enter your signature. The signature will be added to the end of your message before it is sent to your recipient.

---

*If the SMS is too long after adding the signature, the signature will be ignored.*

---

## Storage location

You can press  $\odot$  *Change* to change the preferred storage location of your messages: *SIM card* (Default) or *Mobile phone*.

## Send and save

You can press  $\odot$  to set this option *On* or *Off*. This option allows you to select whether or not to send and save your message.

## MMS

This menu allows you to set your MMS center and personalize your MMS settings. The options include:

### Profiles

You can select or edit the parameters.

### Sender visibility

You can press  $\odot$  *Change* to set this option *On* or *off*. It is used to set if your identity will be visible when MMS is sent.

### Priority

This option allows you to set the priority level of your MMS. You can set *Low*, *Normal* (default) or *High*.

### Delivery report

You can press  $\odot$  *Change* to set this option *On* or *off*. When set to *On*, a report will be sent to notify you if the MMS has been delivered to the recipient.

### **Read report**

You can press  *Change* to set this option *On* or *off*. When set to *On*, a report will be sent to notify you if the MMS has been read by the recipient.

### **Expiry time**

Allows you to select the duration by which your MMS will be stored in the MMS center. You can choose from *6 hours*, *12 hours*, *1 day*, *1 week* or *Maximum* (default).

### **Retrieval**

Allows you to select *Automatic*, *Deferred*, *Auto in home network* when downloading of MMS messages.

### **Auto page turn over**

You can press  *Change* to set this option *On* or *off*.

## 9. My files



This menu allows you to store the files in different folders (*Pictures*, *Sounds*, *Videos*, *Others*) to facilitate more efficient management of files in your phone and the memory card. In addition, you can obtain information regarding your phone and memory card, such as the availability of free memory, memory utilized and total memory size via the *Memory status* option.

After installing a Micro SD card, you can find two folders under *My files*: *Phone* and *Micro SD card*.

### Pictures

When you enter this menu, the photos which you have taken using the phone's camera as well as pictures you have downloaded via MMS, WAP, BT, or USB will be displayed in a list.

1. Select *My files* > (*Phone* or *Micro SD card*) > *Pictures* and press  $\odot$  to enter the menu.
2. Press  $\odot$  *View/Open* to view the selected picture/ open the selected folder or press  $\square$  *Options* to

carry out the following operations to a selected file:

Options	Description
<i>Send</i>	Send the selected file: <i>Via bluetooth</i> and <i>Via MMS</i> .
<i>Advanced</i>	<i>Cut</i> : Similar to copy, but the original file will be deleted. <i>Copy</i> : Copy the selected file to another folder. <i>Edit</i> : Modify or edit the selected picture. Press $\blacktriangleleft/\blacktriangleright$ and $\odot$ to select your edit options.
<i>Rename</i>	Modify the name of the selected file.
<i>Details</i>	Display detailed information of the selected photo, such as last modified date, file size, etc.

**Use** *As contact ID*: If you select this option, the phonebook list will be displayed. After you have selected a contact from the phonebook, press  *Select* to associate the picture to the selected contact.

---

*Only available for picture of 176\*220 or smaller.*

---

*As wallpaper*: If the selected photo is 176\*220 or smaller, it will be displayed as wallpaper in its original size.

**Delete** Delete the selected picture.

**Slide show** If you select this option, the screen will display the full screen view of all the pictures in the form of slideshow every 4 seconds. Press any key to exit from the slide show mode.

**Change view** You can select to view the pictures in *List view*, *Grid view* or *Full screen*.

**Sort** Sort the pictures and folders by name or date.

**Select multiple**

*Select one by one*: select the picture one by one and then *Cut*, *Copy* or *Delete* them.

*Select all*: select all the pictures and then *Cut*, *Copy* or *Delete* them.

3. The folder options include:

- Rename** Modify the name of the selected folder.
- Details** Display detailed information of the selected folder.
- Delete** Delete the selected folder.
- Change view** Select *List view* or *Grid view*.
- Sort** Sort the pictures and folders by name or date.

## Sounds

---

When you enter this menu, the sounds which you have stored or downloaded via MMS, WAP, BT, or USB will be displayed in a list.

1. Select *My files* > (*Phone* or *Micro SD card*) > *Sounds* and press  to enter the menu.
2. Press  *Play/Open* to play the selected audio file/ open the selected folder or press  *Options* to carry out the following operations to a selected file:

**Send** The available options are: *Via bluetooth* and *Via MMS*.

**Advanced** *Cut*: Similar to copy, but the original file will be deleted.

*Copy*: Copy the selected file to another folder

**Use** You can set the audio file: *As ringtone* or *As Contact ID*.

**Rename** Modify the name of the selected file.

**Details** Display detailed information of the selected audio file, such as last modified date, file size, etc.

**Delete** Delete the selected audio file.

**Change view** Select *List view* or *Grid view*.

**Sort** Sort the audios and folders by name or date.

**Select multiple** *Select one by one*: select the audio files one by one and then *Cut*, *Copy* or *Delete* them.

*Select all*: select all the audio files and then *Cut*, *Copy* or *Delete* them.

3. The folder options and their operations are the same as *Pictures* menu.

## Videos

---

When you enter this menu, the videos which you have recorded using the phone's camera as well as videos you have downloaded via MMS, WAP, BT, or USB will be displayed as a list.

1. Select *My files* > (*Phone* or *Micro SD card*) > *Videos* and press  to enter the menu.
2. Press  *Play/Open* to play the selected video/open the selected folder or press  *Options* to carry out the following operations to a selected file:

Options	Description
<i>Send</i>	Send the selected file: <i>Via bluetooth</i> and <i>Via MMS</i> .
<i>Advanced</i>	<i>Cut</i> : Similar to copy, but the original file will be deleted. <i>Copy</i> : Copy the selected file to another folder.
<i>Rename</i>	Modify the name of the selected file.

*Details* Display detailed information of the selected video, such as last modified date, file size, etc.

*Delete* Delete the selected video.

*Change view* You can select to view the video files in *List view*, *Grid view*.

*Sort* Sort the videos and folders by name, date, or size.

*Select multiple* *Select one by one*: select the videos one by one and then *Cut*, *Copy* or *Delete* them.

*Select all*: select all the videos and then *Cut*, *Copy* or *Delete* them.

3. The folder options and their operations are the same as *Pictures* menu.  
Videos are played in the middle of the screen. A status bar is displayed at the top of the screen. The keypad operations when playing videos are as follows:

Key	Operation
	Start/pause the playback.
	Long press to rewind.

- ▶ Long press to fast forward.
- ◀ Exit/return to an upper menu level.
- ⏪ Return to idle screen.

## Others

---

You can save all other files into this folder. The file and folder options and their operations are the same as the [Pictures](#) menu.

## Memory status

---

All memory capacity, used memory capacity and free memory capacity between all memory capacity used in both the mobile phone and memory card will be displayed.

## Memory card

---

The phone has a micro SD memory card slot to increase the phone's memory. The phone supports FAT16 and FAT32 format for 1GB capacity, and supports FAT32 format for 2GB capacity.

Select [My files](#) > [Micro SD card](#) > [Memory card](#). You can select [Uninstall](#) to safely remove memory card from the phone, and select [Format](#) to format it.

For 2GB capacity, in order to ensure the card can be recognized by the phone, please connect the

card to a computer and format it to FAT32 before using it for the first time with X600.

## 10. Business



### Calendar

---

This menu displays the calendar. You can select Day view, Week view or Month view. You can create new appointments, view appointments list, delete or modify appointments in the calendar. The calendar stores the alarm date and time of every event. If the current date and time correspond with the date and time of the event, the phone will emit an alarm (if needed), and the screen will display a prompt to indicate that a new event has arrived. You can create a maximum of 30 events. The list will display part of the contents. Once you have selected an event, you can press to view the detailed information.

1. Enter the menu. Press to access [View](#) or press to access the options menu.
2. The options include: [View week/month](#), [New event](#), [Go to date](#), [Advanced](#).

#### New event

The list of events will be displayed. When you add a new event, you need to enter the corresponding

information of the event, such as subject, location, start date, start time, end date, end time, reminder and repeat method.

---

*If the memory space for events is full, the phone will prompt you that there is no more space.*

---

---

*When editing date and time, the phone will display the default or the selected date and time. You can edit or confirm them directly.*

---

---

*The maximum length of an event is 100 characters.*

---

#### Reminder

*On time, 5 min. before, 15 min. before, 1 hour before, and 1 day before.*

#### Repeat method

The phone provides the following repeat methods: [Once](#), [Daily](#), [Weekly](#), [Monthly](#) and [Annually](#).

---

*When you change the date and time of your phone, the next alert will be repeated based on the modified date and time of the phone.*

---

---

*When you switched off the phone, the organizer alert will be postponed until the next time you*

switch on the phone. For repeated events, only the latest one will be alerted.

---

## Alarm

---

This phone supports 24-hour alarm.  
The available options are:

Options	Description
<i>Simple alarm</i>	A simple alarm rings only once. Set the alarm status to <i>On</i> or <i>Off</i> by pressing <i>Change</i> . When set to <i>On</i> , you need to specify the alarm time and press  to confirm.
<i>Reccurent alarm</i>	A recurrent alarm rings according to the day you specify in a week. Set the alarm status to <i>On</i> or <i>Off</i> by pressing <i>Change</i> . When set to <i>On</i> , you need to specify the <i>Time</i> and <i>Repetition</i> . For example, if you select Sunday and Monday, the alarm clock will ring every Sunday and Monday. Then press  to confirm.
<i>Alarm tone</i>	Select an alarm tone.

*Snooze* The alarm rings again 5 minutes later. Select *On* or *Off*.

## Calculator

---

Your mobile phone has a built in calculator. Enter the numbers with the keypad.

Options	Description
	Addition
	Subtraction
	Multiplication
	Division
	Equals
	To toggle between negative and positive figures.
<i>Options</i> > %	Add a percentage symbol.
<i>Options</i> > <i>Modular</i>	Calculate a remainder of a division.
	Add a decimal point.

---

The maximum length of the numbers and the result is 9 digits. The result of the calculator is indicative.

---

## Voice recorder

---

This menu allows you to record a voice memo. From the main menu, select *Business* > *Voice recorder*. Then you can press  $\square$  to set the *MMS size* and select the *Storage location*. When you set the *MMS size On*, the recording will stop if it exceeds the *MMS size limit*.

To start recording, press  $\ominus$  *Record*. During the process, the recorded time will be displayed in real time. To stop recording, press  $\ominus$  and the file will be saved in *My files* > *Sounds*. Then you could press  $\ominus$  to play the recorded file or press  $\square$  *Options* to access the following options:

Options	Description
<i>New episode</i>	Make another recording.
<i>Delete</i>	Delete the selected file.
<i>Send</i>	Send the selected file.

*Rename* Change the name of the selected file.

## Memo recorder

---

This menu allows you to record a memo. Set the time to play it as a reminder. From the main menu, select *Business* > *Memo recorder*.

To start recording, press  $\ominus$  *New*. During the process, the recorded time will be displayed in real time. To stop recording, press  $\ominus$  and the file will be saved. Then you can edit the *start date*, *start time*, and *reminders* for this recording.

For a recorded memo, press  $\square$  *Options* to access the following options:

Options	Description
<i>Delete</i>	Delete the selected file.
<i>Send</i>	Send the selected file.
<i>Rename</i>	Change the name of the selected file.
<i>Edit</i>	Edit the <i>start date</i> , <i>start time</i> and <i>reminders</i> of the selected file.
<i>Details</i>	View the detailed information of the selected file.

## Stopwatch

---

Your phone features a stop watch and the minimum unit is 0.1 second.

The starting time is 00:00.0, in the format “mm:ss.n”, where mm stands for minutes of the watch, which can be any number from 0 to 59; ss stands for seconds, a number between 0 and 59; n stands for 0.x second, x being any number from 0 to 9. The stopwatch will start the timing when you press ⊖ *Start*. You can pause the timing, press ⊖ *Pause*, to resume, press ⊖ *Go*, to stop the timing, press ☐ *Stop*.

## Countdown

---

This feature is very similar to the alarm clock, except that you will be alerted of the remaining time, and the phone will emit an alarm at the end of the count-down. The alarm tone is the same as your alarm clock.

The minimum time is 1 minute. The format of the time is *hh:mm:ss*, and the maximum time input is 23 hours 59 minutes 59 seconds.

You can edit the time timer and start the countdown by pressing ⊖ *Start*. To stop countdown, press ⊖ *Pause*, to reset, press ☐

*Reset*. and you can exit the menu by pressing the ☐ *Back*.

---

*The count-down timer will switch on automatically and emit an alarm at the end of the count-down even if your phone is in idle mode.*

---

## Unit converter

---

This application allows you to convert many types of units such as exchange rate, area, energy, mass, power, pressure, temperature and volume. Select the type of unit and input the figure and then press ⊖ *Change* to calculate the result.

---

*Press ☐ key to enter the decimal point.*

---

## Firewall

---

This function provides a simple and quick method for you to avoid nuisance calls and SMS. Blacklist contains a list of phone numbers from which you do not wish to receive calls or SMS.

Select *Business > Firewall > Set* and choose between the following options:

- Status: *Status icon*, *Event* or *None*.
- Activate: *On* or *Off*.

To add the phone numbers into the black list, select **Black list**, select **Add new**, then you can carry out the following operations:

Option	Operation
<b>New number</b>	Open the phone number editor, enter the new number and save the number into the black list.
<b>Contacts</b>	Open the phonebook list and select a phone number for saving into the black list.

You can press **↔** to select a particular number in the black list, then press **☐ Options** to carry out the following operations:

<b>Change</b>	Open the phone number editor, to edit the selected number in the black list.
<b>Delete</b>	Delete the selected number in the black list.

## Task

---

This menu allows you to create, store and manage events in your task list.

## Create task

This menu allows you to create a new task. There are 2 types of tasks: **Phone Call** and **Task**. Select **New task** and press **⊖ Select** to access the following options:

<b>Call/Task</b>	Allow you to create a <b>Phone Call</b> or <b>Task</b> . Press <b>↔</b> to select.
<b>Subject</b>	Create a subject for your task.
<b>Call number</b> (Available only in Phone call)	Enter the phone number directly, or press <b>⊖ Select</b> for: <ul style="list-style-type: none"><li>• <b>Contacts</b>: Display the list of contacts for calling.</li><li>• <b>Enter number</b>: Enter the number.</li></ul>
<b>Display on idle</b>	Set <b>On</b> or <b>Off</b> to choose whether the event will display on screen in idle mode. Press <b>↔</b> to select.
<b>Set Reminder</b>	Set <b>On</b> or <b>Off</b> to choose whether you want to receive the alert. When set to <b>On</b> , you need to set the alert date and time. Press <b>⊖</b> to confirm.

After you have finished editing, press **⊖** to **Save** your new task.

## **Manage task**

This menu allows you to manage your tasks . Select a task, then press  to *View* the task or *Call* the contact (depending on if it is the *Task* or *Phone Call*) or press  *Option* to access the following options:

- Mark as (Not) Done*      Mark a tick on the task as done or untick for not done.
- Edit*                Edit the selected task.
- Delete*             Delete the selected task.
- Delete all*         Delete all tasks on the list.

## **STK**

---

The availability of the features in this menu depends on whether or not your SIM card supports STK. If your SIM card supports STK function, the STK menu will be displayed on the screen.

## 11. Contacts



Your phone features two phonebooks. The SIM phonebook is located on your SIM card and the number of entries you can store depends on the SIM card. The second phonebook (Smart phonebook) is integrated in the phone memory and the maximum number of name cards you can store is 2000 (a namecard can consist of a name, 4 phone numbers, groups, email address, address, etc.). The SIM card is the default phonebook, but the entries in the two phonebooks are combined, sorted and displayed as a list. When you add a new contact to your phonebook, the new contact will only be added to the phonebook you have selected.

***You can store up to 2000 name cards, provided other features in the phone such as Calendar, Sounds, Pictures, and Videos, etc. did not use up a large amount of the phone's memory space.***

### New contacts

---

To create a new SIM/phone contact:

Enter new contact      Press  $\ominus$  and select **New Contacts**

Enter contact details      Enter the following for SIM card contacts.

- **Name**
- **Number**

Enter the following for onboard phonebook contacts:

- **Name**
- **General**
- **Mobile**
- **Home**
- **Work** and etc

Store the new contact      Press  $\ominus$  **Save**.

---

***To create a contact, you must enter at least a phone number.***

---

Most of the fields are free-text, which means you can enter alphanumeric data using the text entry functions of your mobile phone (for more

information on text entry, see "Text and number entry" on page 15).

## View contacts

---

In the phonebook, you can display the details of a contact by selecting it. Then press  *View* to view the details of the selected contact or press  *Options* to carry out the following operations:

Options	Description
<i>New contact</i>	Create a new contact.
<i>Send message</i>	Send a <i>SMS</i> or <i>MMS</i> to the contact.
<i>Call</i>	Call the contact.
<i>Edit before call</i>	Change the contact's information before calling the contact.
<i>Call handsfree</i>	Call the contact by handsfree mode.
<i>Delete</i>	Delete the contact.
<i>Add to blacklist</i>	Add the contact into the blacklist.

*Send Contact* Send the selected record: *via SMS* or *via Bluetooth*.

*Copy to phone/SIM* Copy the SIM/phone entry to phone/SIM.

*Move to phone/SIM* Similar to copy, but the source record will be deleted after copying.

*Select multiple* Select one contact at a time or select all contacts.

## View groups

---

The *View groups* feature allows you to organize your contacts so that you can send messages to all the members of the group. From the *Contacts* menu, select *View groups* and the list of groups is displayed.

### View

Select a group and  *View* to add and display the group members or press  *Options* to access the following group options:

Options	Description
<i>Rename</i>	Rename the group.

*Send message* Send an SMS or MMS to members of a group.

*Reset* Restore the group to default settings.

## Special numbers

---

This menu allows you to keep a list of useful numbers such as your own numbers, service numbers, voicemail and SOS numbers.

Options	Description
<i>My number</i>	View, edit or clear your own phone number.
<i>Emergency</i>	Display the emergency phone number.
<i>Voice mail</i>	Dial the number for your voice mail service provider.
<i>Service numbers</i>	This entry of the SIM phonebook allows you to select one of the available services provided by your operator and to copy it into the selected phonebook.

## Advanced

---

This menu provides you with advanced features so that you can view and edit your contacts:

Options	Description
<i>Choose contact list</i>	<ul style="list-style-type: none"><li>• Default contact list: Switch contact list between <i>SIM</i>, <i>Phone</i> or <i>All</i>.</li><li>• Default contact location: Select the new contact entry saved on the SIM or phone memory.</li></ul>
<i>Copy contact</i>	<i>Copy to SIM</i> : Copy all the entries to SIM. <i>Copy to phone</i> : Copy all the entries to Phone.
<i>Move contact</i>	<i>Move to SIM</i> : Move all the entries to SIM. <i>Move to phone</i> : Move all the entries to Phone.
<i>Delete all contacts</i>	Delete all contacts.

## 12. Profiles



Your mobile phone has been preconfigured with the following modes:

- *Personal (default)*
- *Car*
- *Flight*
- *Home*
- *Meeting*
- *Outdoors*
- *Silent*

You can activate and modify all the modes, except the *Flight* mode and *Silent* mode. These 2 modes can only be activated and viewed.

The profiles and their respective parameters are as follows:

Personal	<i>Ring volume</i>	Level 9
	<i>Ringtones</i>	Default
	<i>Alert type</i>	Vibrate and ring
	<i>Key sound</i>	On
	<i>Backlight level</i>	Level 3

Car	<i>Ring volume</i>	Level 8
	<i>Ringtones</i>	Default
	<i>Alert type</i>	Vibrate and ring
	<i>Key sound</i>	On
Flight	<i>Backlight level</i>	Level 4
	<i>Ring volume</i>	No volume
	<i>Alert type</i>	None
	<i>Key sound</i>	Off
Home	<i>Backlight level</i>	Level 3
	<i>Ring volume</i>	Level 4
	<i>Ringtones</i>	Default
	<i>Alert type</i>	Vibrate and ring
	<i>Key sound</i>	On
	<i>Backlight level</i>	Level 3

Meeting	<i>Ring volume</i>	Silence
	<i>Ringtones</i>	Default
	<i>Alert type</i>	Vibrate
	<i>Key sound</i>	Off
	<i>Backlight level</i>	Level 4
Outdoors	<i>Ring volume</i>	Level 9
	<i>Ringtones</i>	Default
	<i>Alert type</i>	Vibrate and ring
	<i>Key sound</i>	On
	<i>Backlight level</i>	Level 4
Silent	<i>Ring volume</i>	Silence
	<i>Alert type</i>	None
	<i>Key sound</i>	Off
	<i>Backlight level</i>	Level 2

### Profile selection

To select a different profile:

Go to *Profiles* menu      Press  $\odot$  to enter the main menu from the idle mode and select *Profiles*.

Select the desired profile.      Press  $\blacktriangle$  or  $\blacktriangledown$  and  $\odot$  *Select*.

To change the settings of a profile:

Press  $\square$  *Change*. You may select:

Options	Description
<i>Ring volume</i>	Select from 9 volume levels.
<i>Ringtones</i>	Select the ringtone for <i>Calls</i> , <i>Alarm 1</i> , <i>Alarm 2</i> , <i>Alarm 3</i> , <i>Calendar</i> , <i>Messages</i> or <i>Cell info</i> .
<i>Alert type</i>	Select an alert type: <i>Ring only</i> , <i>Vibrate only</i> , <i>Vibrate and ring</i> , <i>Vibrate then ring</i> or <i>Silent</i> .
<i>Key sound</i>	Set the key sound <i>On</i> or <i>Off</i> .
<i>Backlight level</i>	Select a backlight level from level 1 to level 4.

## 13. Connectivity



This menu provides you with more features to set up a connection with these external devices.

### Bluetooth

---

Your phone supports Bluetooth wireless technology, allowing connection to a compatible Bluetooth device. To ensure interoperability between other Bluetooth devices, please check with the manufacturers of other devices. The Bluetooth connection can be subjected to interference from obstructions such as walls or other electronic devices.

To use Bluetooth connection, the device with which you want to establish a connection must support Bluetooth function. Please contact the device's manufacturer or its accompanied documentation.

#### Establish a Bluetooth connection

To activate, press  to enter the main menu from the idle mode and then select *Connectivity* > *Bluetooth*. On the Bluetooth screen, select *Activate*. Next, select *Search for devices*. When the list of

devices appears, select the device you wish to establish a connection with.

---

*If you do not intend to use the Bluetooth feature for some time, you should deactivate it in order to conserve battery power.*

---

### Bluetooth menu

Options	Description
<i>Activate</i>	Turn Bluetooth feature on or off.
<i>Search for devices</i>	Search for the external devices that you can connect to.
<i>My devices</i>	Display the bluetooth devices that you can connect to. You can select the desired device by pressing  in the devices list. You can also open the <i>Options</i> menu of the device. The options are: <i>Connect/Disconnect</i> (if applicable) <i>Browse files</i> (if applicable) <i>Activate/Deactivate stereo</i> (if applicable) <i>Rename</i> <i>Delete</i>

## Settings

Select to display more features:

- **My name:** edit the name of the device
- **Visibility:** choose to show or hide the device by select toggle **On** or **Off**
- **My profiles:** lists the phone's available profiles

When searching for a device, you are presented with a list of any devices discovered within the range of your Bluetooth-enabled phone. As soon as you select a device and a connection is made, you are prompted to enter a passkey in order to pair with the device. This passkey is supplied by the manufacturer of the other Bluetooth device. Refer to its documentation for further information. The passkey feature ensures that only legitimate connections are allowed to connect either to your device or to the selected device.

## USB function

Connect your phone to a PC via USB cable, and your phone will then behave like a USB drive. With your phone, you can access files on your memory card. You can upload and download music, videos and

pictures via the USB cable, and the size of file transfer is unlimited until your memory is full.

---

***When copying files from your PC to phone, first insert a Micro-SD memory card into your phone.***

---

***When the transfer is finished, please make sure that you safely remove your device based on the instruction of your computer.***

---

## Using PhilipsPhoneTools

Besides, your phone can perform PC connections with the supplied PhilipsPhoneTools. PhilipsPhoneTools offers instant synchronization between your phone and your computer, and enables you to backup your mobile phone data and recover the data saved in the computer, receive SMS and edit your mobile phone contacts

### ***Installing PhilipsPhoneTools on your PC***

1. Insert the supplied the PhilipsPhoneTools into the CD drive.
2. Run the Setup.exe program.
3. Make selections as prompted, and installation starts automatically.

---

*During the installation, interruption may occur when your PC system detects the new software. Press Continue Anyway repeatedly until the installation resumes.*

---

### **Connecting your Phone to the PC**

1. Check that the Phone Setup wizard starts. If necessary, double click the PhilipsPhoneTools icon.
2. Connect your phone to the PC as prompted.
3. On your phone, select *Connectivity* > *USB function* > *PC Sync* from the main menu.  
A functional menu appears on your PC screen.

## 14. Calls



Most options described in this chapter are operator and/or subscription dependent and require either a PIN2 code or a phone code. For more information on PIN codes, see see "General" on page 70.

### View calls

---

This menu provides you with a list of calls you have missed, answered and made. The calls include *All calls*, *Missed calls*, *Answered call*, *Outgoing calls* and *Rejected calls*, which are displayed in chronological order with the most recent call at the top of the list. Select a call from one of the lists and press  *Dial* to call or press  *Options* to access the following:

Options	Description
<i>View</i>	View the detailed information of the selected call.
<i>Save</i>	Save the number if the number is not in the contacts list.

*Save to existing* Save the number in the current the contacts list.

*Send messages* Send a message to the selected number. You can send by *SMS* or *MMS*.

*Delete* Delete the selected number from the list.

*Delete* Delete all numbers from the list.

*Dial* Call the selected number.

*Add to blacklist* To add the phone number into the blacklist, see see "Firewall" on page 55.

*Edit number before dialing* Open the contacts list and edit the number if it is in the contacts list.

### Call options

---

This menu allows you to configure the call settings:

Options	Description
---------	-------------

### Auto answer

Turn *Auto answer* on/off. When this function is on, the incoming call will be answered automatically after 10 seconds.

### Any key answer

Turn *Any key answer* on/off. When this function is on, you can answer incoming calls by pressing any key, except  $\sqrt{\square}$ ,  $\square$ .

### Minute reminder

Select *On* or *Off* to activate or deactivate the minute reminder during a call. The default is *Off* and the default setting is 45 seconds.

### Call services

The available options include:

- *Call time*: Display the duration of your calls and their charges: *Total incoming calls*, *Total outgoing calls* and *Total calls*.
- *Call waiting*: Select *Enable* or *Cancel*, or check *Status*.

---

*This feature is network/subscription dependent.*

---

- *Own ID*: Select *Show ID* or *Hide ID* or *Set by network* to determine your phone number or identity will be displayed or not to the called party.
- *Caller ID*: To check your operator setting of showing the identity of your caller.

---

*This feature is network/subscription dependent.*

---

- **Cost settings:** This option is available only when the charge information is included in your SIM card. You can view information of the current call and all recent calls. You need to enter the PIN2 code to manage, maximum cost credit and unit rate.

### Call forward

Set the following call divert options: *All calls*, *If no reply*, *If out of reach*, *If busy*.

- When *All calls* is on, all incoming calls will be diverted to the pre-set number without any reminder.
- When *If no reply* is on, incoming calls will be diverted if the user does not answer.
- When *If out of reach* is on, incoming calls will be diverted to the pre-set number when the user is not connected to the network.
- When *If busy* is on, calls will be diverted if the user is already online or if the call is rejected.
- You can also check the *Status* of your call diverts or *Cancel all* call diverts.

### Call barring

This menu allows you to limit the use of your phone to specific calls by preventing the reception or making of different types of calls. To activate call barring, you need to enter a communication limit code. This PIN2 code will then be sent to the network for validation.

---

**Note that this operation only supports GSM calls.**

---

The types of calls you can bar are as follows:

- All outgoing calls
- All international calls
- Only here & home
- All incoming calls

You can also check the *Barring status* of your call barring or *Cancel barring*.

### Restricted dialing

This menu allows you to set the password to prevent the phone from being used by another person.

### IP number

Dial IP prefix of your network operator.

## Clear history

---

This menu allows you to clear the call history in: *Delete all/Missed calls/Answered calls/Outgoing calls/Rejected calls*. Press  *Select* to confirm deletion and  *Back* to cancel deletion.

## 15. Settings



You can configure your X600 mobile phone to best suit your usage preference. You can configure the following settings: [General](#), [Display](#), [Sounds](#) and [Connectivity](#).

Enter the menu      Press  to enter the main menu from idle mode and select [Settings](#).

Select a settings menu      Press  or .

### General

---

This menu allows you to configure some general settings:

Options	Description
<a href="#">Active flip</a>	Press  to set <a href="#">On</a> or <a href="#">Off</a> . When you select <a href="#">On</a> , you can answer an incoming call simply by opening the flip.

### Languages

Set the display language of the phone.

### Time & date

- [Display time](#): Select [On](#) or [Off](#). When you select [On](#), the time information will be displayed in the idle screen.
- [Set time](#): Set the time in the format [HH:MM](#).
- [Set date](#): Set the date.
- [Time format](#): Set the time format as [24 hours](#) or [12 hours](#).
- [Date format](#): Set the date format as [YYYY/MM/DD](#), [YYYY.MM.DD](#), [DD.MM.YYYY](#), [YYYY-MM-DD](#) or [DD-MM-YYYY](#).
- [International clock](#): Go to the international clock menu and change the time zone.
- [Power-on time](#): Set a time for the phone to be switched on. You can select [On](#) or [Off](#). When you select [On](#), you need to enter the time you want your phone to be switched on.
- [Power-off time](#): same as above.

## Security

- **PIN protection:** Select *On* or *Off*. When you select *On*, you need to enter the PIN code when you switch on the phone.

***The default PIN code is network dependent on your service provider. Please contact your service operator for the PIN information.***

- **Change PIN/PIN2:** You can modify the password for PIN, PIN2, safeguard and phonelock.
- **Safeguard:** You can safeguard important information such as messages, contacts on your phone by activating safeguard. You can also change the safeguard password.
- **Change safeguard password:** You can modify the password for PIN, PIN2, safeguard and phonelock.

***The default safeguard and phonelock password is 1234.***

## Shortcuts

Displays a list of shortcut features. You can set a new shortcut key by establishing a link between a certain feature and a numeric or navigation key. You can also change or delete an existing shortcut key.

## Speed dial

This menu allows you to quickly dial the number stored in your phonebook. Select a number (from 2-9) on the list to configure. You can set a maximum of 8 speed dial numbers, so that a long press on the numeric key will dial the number associated with that numeric key.

## Default storage

Set the default storage location: *Phone memory* or *Memory card* for different applications.

## Memory status

You can check the memory status of *Contacts*, *Messaging* and *My files*. You can also check the memory status of *Memory card* if it is inserted.

## Mainmenu style

Select the browse style as *List* or *Grid*.

Restore your phone settings to the default values.

## Display

---

You may configure your phone with different display settings:

Options	Description
<i>Wallpaper</i>	Turn the wallpaper display <i>On</i> or <i>Off</i> .
<i>Themes</i>	Select from 2 themes.
<i>Backlight level</i>	Select from 4 backlight levels. You can select the backlight level by pressing + or - keys. Press $\ominus$ to confirm.
<i>Backlight duration</i>	Select the backlight duration from <i>60 seconds</i> , <i>30 seconds</i> and <i>15 seconds</i> .
<i>Greeting</i>	Turn greetings <i>On</i> or <i>Off</i> . When you select <i>On</i> , you can edit the greetings message.

---

***The maximum length of greetings is 20 Chinese words or 40 English characters.***

---

## Sounds

---

You can set your phone to operate with different sound profiles. For details, see [?\\$paratext>?](#) on page 73.

Options	Description
<a href="#">Alert type</a>	You can select <a href="#">Ring only</a> , <a href="#">Vibrate only</a> , <a href="#">Vibrate &amp; ring</a> , <a href="#">Vibrate then ring</a> or <a href="#">Silent</a> .
<a href="#">Ringtones</a>	Select the ringtone for <a href="#">Calls</a> , <a href="#">Alarm 1</a> , <a href="#">Alarm 2</a> , <a href="#">Alarm 3</a> , <a href="#">Calendar</a> and <a href="#">Messages</a> , <a href="#">Cell info</a> .
<a href="#">Ring volume</a>	Select from 9 volume levels.
<a href="#">Key sound</a>	Turn the key sound <a href="#">On</a> or <a href="#">Off</a> .
<a href="#">Shutter sound</a>	Select from 3 shutter sounds. You can also select <a href="#">Off</a> .
<a href="#">Low battery alert</a>	Turn the warning <a href="#">On</a> or <a href="#">Off</a> .

---

***If you have downloaded your own ring tones and have selected such a ring tone to be the alarm alert, then after you set the alarm and switched off the phone, the alert tone will be changed back to the original factory settings.***

***This does not apply if the ring tone you have chosen is one that comes as default with your phone.***

---

## Connectivity

---

### Call options

For more information, see [?Call options?](#) on page 67.

### Message settings

For more information, see [?Settings?](#) on page 47.

### Network settings

The network name will be displayed on the idle screen. If the phone is not able to identify the network name, it will display the country code and the network code of the unknown network.

### Select network

It will vary according to the search mode you have selected. If you select [Automatic](#), the network will be searched automatically. If you select [Manual](#), the search will commence only when you confirm to start searching.

### Search mode

You can select [Automatic](#) or [Manual](#).

## Preferred Networks

Preferred network list is stored in the SIM card. It specifies the priority by which your phone will register to the available network during automatic registration.

1. In idle mode, press  $\odot$  to enter the main menu.
2. Select *Settings* > *Connectivity* > *Network settings* > *Preferred networks*.
3. Press  $\odot$  *Select* to enter the preferred network list. The most preferred network will be at the top of the list.
4. Press  $\blacktriangle/\blacktriangledown$  to select a certain network.
5. You can then press  $\odot$  to *Insert* or press  $\square$  *Option* and select to *Add to end* or *Delete* the selected network.

## Browser

Various parameters relative to browser can be set under this option, including WAP parameters and Push message.

## Connections

### GPRS profiles

This menu allows you to configure a GPRS (General Packet Radio Service) connection to the network. The available GPRS settings are:

Options	Description
---------	-------------

<i>Profile name</i>	To name the current profile
<i>APN</i>	To enter GPRS APN.
<i>Login</i>	To enter a login name.
<i>Password</i>	To enter the password.

### GPRS info

This feature allows you to monitor the amount of data transferred during GPRS connection.

## Icons & Symbols

In idle mode, several icons and symbols can be displayed on the main screen. The status, network and battery icons are displayed all the time. The rest of the icons are displayed if the feature is available, and not displayed if the feature is unavailable.

*If the network symbol is not displayed, it implies that the network is currently unavailable. You may be in a bad reception area; moving to a different location may help.*



**Network** - Network icon comprises of 2 portions. The left portion indicates whether or not your phone is already registered with a network, and the right portion indicates signal strength in 5 levels (from no signal to strongest).



**Battery** - Indicates battery level with 5 battery level indicator bars. When charging, a scrolling icon will be displayed.



**International roaming** - Displayed when your phone is registered to a network other than your own.



**Whether to log on GPRS** - There are 2 GPRS status which are mutually exclusive: GPRS network is available but not in use; or GPRS network is available and in use. The icon will be displayed only when you have logged on to GPRS.



**MMS** - Indicates there is a MMS message.



**WAP Push message** - Indicates there is a WAP push message. Go to **Browser** > **Push Inbox** to check it.



**Voicemail** - Indicates voice messages that have not been heard.



**Alarm Clock** - Indicates that the alarm clock is activated.



**Vibration** - Your phone will vibrate when there is an incoming call or when the alarm clock rings.



**Firewall** - Indicates that firewall feature is activated.



*New event* - You have a new event.



*Miss call* - Indicates there is a miss call.



*Call Divert* - Indicates that the call divert function is activated.



*Meeting* - Indicates that silent mode is activated.



*Memory card* - Indicates the memory card is in use.



*Bluetooth* - Feature is activated.

---

# Precautions

## Radio Waves



Your cellular mobile phone is a **low power radio transmitter and receiver**. When it is operating, it sends and receives radio waves. The radio waves carry your voice or data signal to a base station that is connected to the telephone network. The network controls the power at which the phone transmits.

- Your phone transmits/receives radio waves in the GSM frequency (900 / 1800 / 1900 MHz).
- The GSM network controls transmission power (0.01 to 2 watts).
- Your phone complies with all relevant safety standards.
- The CE mark on your phone shows compliancy with European electromagnetic compatibility (Ref. 89/336/EEC) and low voltage directives (Ref. 73/23/EEC).

Your cellular mobile phone is your responsibility. To avoid damage to yourself, to others or to the phone itself, read and follow all the safety instructions and make them known to anyone

borrowing your phone. Furthermore to prevent unauthorized use of your phone:



Keep your phone in a safe place and keep it out of small children's reach.

Avoid writing down your PIN code. Try to remember it instead.

Switch off the phone and remove the battery if you are going to leave it unused for a long time.

Change your PIN code after purchasing the phone and to activate call restriction options.



The design of your phone complies with all applicable laws and regulations. However your phone may cause interference with other electronic devices. Consequently you should follow all **local recommendations and regulations** when using your cellular phone both at home and when away. **Regulations on the use of cellular phones in vehicles and aircraft are particularly stringent.**

Public concern has been focused for some time on the possible health risks for users of cellular phones. The current research on radio wave technology, including the GSM technology, has been reviewed and safety standards have been drawn up to ensure protection from exposure to radio wave energy.

Your cellular telephone **complies with all applicable safety standards** and the Radio Equipment and Telecommunications Terminal Equipment Directive 1999/5/EC.

## Always switch off your phone

---

Inadequately protected or **sensitive electronic equipment** may be affected by radio energy. This interference can lead to accidents.



Before boarding an **aircraft** and/or when packing the phone in your luggage: the use of mobile phones in an aircraft may be dangerous for the operation of the aircraft, disrupt the mobile phones network and may be illegal.



In **hospitals**, clinics, other health care centres and anywhere else where you may be in the close vicinity of **medical equipment**.



In areas with a potentially **explosive atmosphere** (e.g. petrol stations and also areas where the air contains dust particles, such as metal powders).

In a vehicle transporting flammable products (even if the vehicle is parked) or a vehicle powered by

liquefied petroleum gas (LPG), check first that the vehicle complies with the applicable safety rules. In areas where you are requested to turn off radio transmitting devices, such as quarries or other areas where blasting operations are in progress.



Check with the vehicle manufacturer that **electronic equipment** used in your vehicle will not be affected by radio energy.

## Pacemakers

---

If you have a **pacemaker**:

- Always keep the phone more than 15 cm from your pacemaker when the phone is switched on, in order to avoid potential interference.
- Do not carry the phone in a breast pocket.
- Use the ear opposite to the pacemaker to minimize the potential interference.
- Switch off your phone if you suspect that interference is taking place.

## Users of hearing aids

---

If you are a user of a **hearing aid**, consult your physician and hearing aid manufacturer to learn whether your particular device is susceptible to cellular phone interference.

## Improved performance

---

In order to **improve the performance of your phone**, reduce radio energy emission, **reduce battery consumption and ensure safe operation adhere to the following guidelines:**



For the optimal and satisfactory operation of the phone, you are recommended to use the phone in the normal operating position (when not using in hands-free mode or with a hands-free accessory).

- Do not expose your phone to extreme temperatures.
- Treat the phone with care. Any misuse will void the International Guarantee.
- Do not immerse the phone in any liquid; if your phone is damp, switch it off, remove the battery, and let them dry for 24hrs before using them again.
- To clean the phone, wipe it with a soft cloth.
- Placing and receiving calls consumes the same amount of battery energy. However, the mobile consumes less energy in idle screen when kept in the same place. When in idle screen and while you are moving, your phone consumes energy to transmit updated location information to the network. Setting the backlight for a shorter

period of time as well as avoiding unnecessary navigating in the menus will also help to save the battery's energy for longer phoning and stand-by performances.

## Battery information

---

- Your phone is powered by a rechargeable battery.
- Use specified charger only.
- Do not incinerate.
- Do not deform or open the battery.
- Do not allow metal objects (such as keys in your pocket) to short circuit the battery contacts.
- Avoid exposure to excessive heat (>60°C or 140°F), moisture or caustic environments.



You should only use Philips authentic battery and accessories, as the use of any other accessories may damage your phone and may be dangerous, and will make all guarantees for your Philips phone null and void. The use of an incorrect type of battery may also cause an explosion.

Make sure damaged parts are replaced immediately by a qualified technician and that they are replaced with genuine Philips replacement parts.

## **Do not use your phone while driving**



Speaking on the telephone while driving lowers your concentration, which can be dangerous. Adhere to the following guidelines:

- Give your full attention to driving. Pull off the road and park before using the phone.
- Respect the local regulations in countries where you drive and use your GSM phone.
- If you want to use your phone in a vehicle, install the hands-free car kit which is designed for that purpose.
- Ensure that your phone and car kit do not block any air bags or other security devices fitted in your car.

The use of an alarm system to operate a vehicle's lights or horn to indicate incoming phone calls is prohibited on public roads in some countries. Check local regulations.

### **EN60950 Norm**

In case of hot weather or after a prolonged exposure to the sun (e.g., behind a window or a windscreen), the temperature of your phone's casing might increase, especially when featuring a metallic finish. Be very careful in this case when picking up your

phone and also avoid using it with an ambient temperature over 40°C.

For your phone, the socket-outlet shall be installed near the phone and shall be accessible.

## **Environmental care**



Remember to observe the local regulations regarding the disposal of the packaging materials, exhausted batteries and old phone and please promote recycling.

Philips has marked the battery and packaging with standard symbols designed to promote the recycling and appropriate disposal of your eventual waste.



The labelled packaging material is recyclable.



A financial contribution has been made to the associated national packaging recovery and recycling system.



The plastic material is recyclable (also identifies the type of plastic).

## **WEEE Marking in the DFU: “Information to the Consumer”**

---

### Disposal of your old product

Your product is designed and manufactured with high quality materials and components, which can be recycled and reused.



When this crossed-out wheeled bin symbol is attached to a product it means the product is covered by the European Directive 2002/96/EC

Please inform yourself about the local separate collection system for electrical and electronic products.

Please act according to your local rules and do not dispose of your old products with your normal household waste. The correct disposal of your old product will help prevent potential negative consequences for the environment and human health.

### **FCC Compliance Statement**

---

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection

against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation.

If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.

Any changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

# Troubleshooting

## ***The phone does not switch on***

Remove/reinstall the battery. Then charge the phone until the battery icon stops scrolling. Unplug from charger and try to switch on the phone.

## ***Your phone doesn't return to the idle screen***

Long press the hangup key or switch off the phone, check that the SIM card and the battery have been installed correctly and switch it on again.

## ***The network symbol is not displayed***

The network connection is lost. Either you are in a radio shadow (in a tunnel or between tall buildings) or you are outside the network coverage area. Try from another place, try to reconnect to the network (especially when abroad), check that the antenna is in place if your mobile has an external antenna, or contact your network operator for assistance/information.

## ***The display doesn't respond (or the display responds slowly) to key presses***

The display responds more slowly at very low temperatures. This is normal and does not affect the operation of the phone. Take the phone to a

warmer place and try again. In other cases, please contact your phone supplier.

## ***Your battery seems to over heat***

You might be using a charger that was not intended for use with your phone. Make sure you always use the Philips authentic accessory shipped with your phone.

## ***Your phone doesn't display the phone numbers of incoming calls***

This feature is network and subscription dependent. If the network does not send the caller's number, the phone will display *Call 1* or *Withheld* instead. Contact your operator for detailed information on this subject.

## ***You can't send text messages***

Some networks don't allow message exchanges with other networks. First check that you entered the number of your SMS centre, or contact your operator for detailed information on this subject.

## ***You have the feeling that you miss some calls***

Check your call divert options.

***The display shows INSERT SIM***

Check that the SIM card has been inserted correctly. If the problem remains, your SIM card may be damaged. Contact your operator.

***When attempting to use a feature in the menu, the mobile displays NOT ALLOWED***

Some features are network dependent. Therefore, they are only available if the network or your subscription supports them. Contact your operator for detailed information on this subject.

***Your phone is not charging***

If your battery is completely flat, it might take several minutes of pre-charge (up to 10 minutes in some cases) before the charging icon is displayed on the screen.

## Philips Authentic Accessories

Some accessories, such as a standard battery and a charger, are included as standard accessories in your mobile phone package. Additional accessories may also be provided or sold separately. Package contents may therefore vary.

*To maximize the performance of your Philips phone and not to void the warranty, always purchase Philips Authentic Accessories that are specially designed for use with your phone. Philips Consumer Electronics cannot be held liable for any damages due to use with non authorized accessories.*

### Charger

---

Charges your battery in any AC outlet. Small enough to carry in a briefcase/handbag.

### Data connect kit

---

Provides easy data connection to your Philips mobile phone. The USB cable enables high-speed communication between your phone and your computer. The provided software allows you to download pictures and melodies and to synchronize your contacts and appointments.

### Deluxe Headset

---

The integrated answer button offers you a simple way to answer your calls. Simply answer an incoming call by pressing the button or long press to reject the incoming call.

# Trademark Declaration



Tegic Euro. Pat.  
App. 0842463

T9<sup>®</sup> is a trademark of Tegic Communications Inc.



Bluetooth<sup>™</sup> is a trademark owned by telefonaktiebolaget L M Ericsson, Sweden and licensed to Philips.

**PHILIPS**



PHILIPS and PHILIPS' Shield Emblem are registered trademarks of Koninklijke Philips Electronics N.V. manufactured by Shenzhen Sang Fei Consumer Communications Co., Ltd. under license from Koninklijke Philips Electronics N.V.

# Specific Absorption Rate Information

## International standards

### THIS MOBILE PHONE MEETS THE INTERNATIONAL RECOMMENDATIONS FOR EXPOSURE TO RADIO WAVES

Your mobile phone is a radio transmitter and receiver. It is designed and manufactured not to exceed the limits for exposure to radio frequency (RF) energy defined by the international standards. These recommendations have been established by the International Commission on Non-Ionizing Radiation Protection (ICNIRP) and, the Institute of Electrical and Electronics Engineers (IEEE) that forecast a substantial safety margin for assuring the protection of all persons, regardless of age and health.

The exposure recommendations for mobile phones use a measurement unit known as the Specific Absorption Rate (SAR). The SAR limit recommended by the ICNIRP for the mobile phones used by the general public is **2.0W/kg averaged over ten grams of tissue** and, is **1,6W/kg averaged over one gram of tissue** by IEEE Std 1528 for the head.

Tests for SAR have been conducted using recommended operating positions with the mobile phone transmitting at its highest certified power level in all tested frequency bands. Although the SAR is determined at the highest certified power level, the actual SAR levels of the mobile phone while operating are generally below the maximum SAR value. This is because the phone is designed to operate at multiple power levels so as to use only the power required to reach the network. In general, the closer you are to a base station antenna, the lower the power output.

While there may be differences between the SAR levels of various phones and at various positions, they all meet the international protection standards for exposure to radio waves.

The highest SAR value for this Xenium X600 model phone when tested for compliance against the standard was 0,279 W/kg for ICNIRP recommendation and 0,391 W/kg for IEEE Std 1528.

For limiting the radio waves exposure, it is recommended to reduce the mobile phone call duration or to use a headset. The purpose of those precautions is to take the mobile phone away from the head and the body.

For body worn operation, this phone has been tested and meets FCC RF exposure guidelines when used with an accessory that contains no metal and that positions the handset a minimum of 1.5cm from the body. Use of other accessories may not ensure compliance with FCC RF exposure guidelines.

## Limited warranty

### 1. What Does This Limited Warranty Cover?

Philips warrants to the original retail purchaser (“Consumer” or “You”) that this Philips cellular product and all accessories originally provided by Philips in the sales package (“Product”) are free from defects in materials, design and workmanship under normal use in accordance with the operating instructions and pursuant to the following terms and conditions. This limited warranty extends only to the Consumer for Products purchased and used in the original country of purchase. The limited warranty is valid only in Philips’ intended country of sales of the product.

### 2. How Long is The Limited Warranty Period?

The limited warranty period for the Product extends for ONE (1) YEAR from the date of purchase of the Product, documented by valid proof of purchase. The limited warranty for original Philips rechargeable battery extends for six (6) months from the date of purchase.

### 3. What Will Philips Do if The Product is Not Free From Material Defects in Materials and

### Workmanship During The Limited Warranty Period?

During the limited warranty period, Philips or its authorized service representative will, at its option either repair or replace, without charge for parts or labour, a materially defective Product with new or refurbished parts or Product and return such repaired or replaced Product to the Consumer in working condition. Philips will retain defective parts, modules or equipment.

Repaired or replaced Product will be covered by this limited warranty for the balance of the original limited warranty period or ninety (90) days from the date of repair or replacement whichever is longer. Repair or replacement of Product, at Philips’ option is your exclusive remedy.

### 4. What is Not Covered By This Limited Warranty?

This limited warranty does not cover:

- a) Product that has been subjected to misuse, accident, shipping or other physical damage, improper installation, abnormal operation handling, neglect,

- inundation, fire, water or other liquid intrusion; or
- b) Product that has been damaged due to repair, alteration, or modification by anyone not authorized by Philips; or
  - c) Product that has reception or operation problems caused by signal conditions, network reliability or cable or antenna systems; or
  - d) Product defects or problems caused by uses with non-Philips products or accessories; or
  - e) Product which warranty/quality stickers, product serial number or electronic serial number has been removed, altered or rendered illegible; or
  - f) Product purchased, used, serviced, or shipped for repair from outside the original country of purchase, or used for commercial or institutional purposes (including but not limited to Products used for rental purposes); or
  - g) Product returned without valid proof of purchase or which proof of purchase has been altered or is illegible.
  - h) Normal wear and tear or Force Majeure.
5. How Do You Get Warranty Service?
- a) Return the Product to an authorized service center of Philips. You may contact the local Philips office for the location of the nearest authorized service center.
  - b) The SIM card must be removed from the Product before it is given to Philips. Philips assumes no liability for damaged or loss of the SIM card or the data contained therein.
  - c) If the Product failure is not covered by this limited warranty, or this limited warranty is inapplicable, void or invalid due to any terms and conditions stated herein, the Consumer will be charged for the cost of repair or replacement of the Product and all other related cost incurred in repairing or replacing the Product.
  - d) IMPORTANT - you are required to return the Product together with a valid proof of purchase which must identify the point of purchase, date of purchase, Product model and Product serial number clearly.
6. Other Limitation: This Warranty is The Entire Agreement.

EXCEPT FOR THE EXPRESS WARRANTIES SET FORTH ABOVE AND THOSE IMPLIED BY LAW AND WHICH CANNOT BE EXCLUDED OR MODIFIED BY

AGREEMENT, PHILIPS PROVIDES NO OTHER WARRANTY WHETHER EXPRESS OR IMPLIED (WHETHER BY STATUTE, UNDER THE OPERATION OF LAW OR OTHERWISE) AND SPECIALLY DISCLAIMS ANY WARRANTY OF SATISFACTORY QUALITY MERCHANTABILITY OR FITNESS FOR A PARTICULAR PURPOSE. PHILIPS' TOTAL LIABILITY FOR DAMAGES RELATING TO OR ARISING OUT OF THE PURCHASE OR USE OF THE PRODUCT, REGARDLESS OF THE TYPE OR CAUSE OF SUCH DAMAGE OR THE FORM OR CHARACTERISATION OF THE CLAIM ASSERTED (E.G. CONTRACT OR TOPIT), SHALL NOT EXCEED THE ORIGINAL PURCHASE PRICE PAID FOR THE PRODUCT.

HOWEVER IN NO EVENT SHALL PHILIPS BE LIABLE FOR ANY PUNITIVE, SPECIAL, INCIDENTAL, INDIRECT OR CONSEQUENTIAL DAMAGES (INCLUDING BUT NOT LIMITED TO THE LOSS OF USE, LOSS OF TIME, INCONVENIENCE, COMMERCIAL LOSS, LOST PROFITS, LOST BUSINESS OPPORTUNITIES, COST OF SUBSTITUTION OF GOODS OR SERVICES, INVESTMENTS, DAMAGE TO GOODWILL OR REPUTATION, OR LOSS OF DATA AND

CLAIMS BY THIRD PARTIES) RESULTING FROM PURCHASE OR USE OF THE PRODUCT, TO THE FULLEST EXTENT ALLOWED BY LAW, WHETHER OR NOT PHILIPS HAS BEEN ADVISED OF THE POSSIBILITY OF SUCH DAMAGES. THESE LIMITATIONS SHALL APPLY NOTWITHSTANDING THE FAILURE OF THE ESSENTIAL PURPOSE OF ANY LIMITED REMEDY.

This limited warranty represents the complete and exclusive agreement between the Consumer and Philips with respect to this cellular Product and it supercedes all prior agreements between the parties, oral or written, and all other communications between the parties relating to the subject matter of this limited warranty. No carrier, retailer, agent, dealer, employee, thereof, or employee of Philips is authorized to make modifications to this limited warranty and you should not rely on any such representation.

This limited warranty does not affect the Consumer's statutory rights under applicable national laws in force.

# Declaration of conformity

We,

**Shenzhen Sang Fei Consumer Communications Co., Ltd.**  
**11 Science and Technology Road,**  
**Shenzhen Hi-tech Industrial Park,**  
**Nanshan District, Shenzhen 518057**  
**China**

declare under our sole responsibility that the product

**Xenium X600**

Cellular Mobile Radio GSM 900/1800/1900  
TAC: 35520202

to which this declaration relates, is in conformity with the following Standards:

**SAFETY : EN 60950-1: 2001+A11:2004**

**HEALTH: EN50360: 2001**

**EMC: ETSI EN301 489-7 v 1.2.1; ETSI EN 301 489-17 v1.2.1**


**SPECTRUM: ETSI EN 301 511 v9.0.2; ETSI EN 300 328 v1.6.1**

We hereby declare that all essential radio test suites have been carried out and that the above named product is in conformity to all the essential requirements of Directive 1999/5/EC.

The conformity assessment procedure referred to in Article 10 and detailed in Annex V of Directive 1999/5/EC has been followed related to articles 3.1 and 3.2 with the involvement of the following Notified Body: CETECOM ICT Services GmbH, Unterturkheimer Strabe6-10, 66117, Saarbrucken, Germany.

Identification mark: **0682**

June 12, 2008



Quality Manager