

FW-D750/21M, FW-D750/21A Firmware Upgrade

Firmware Upgrade

We have developed a firmware upgrade to improve your product.

This firmware version improves: [Click here for more details](#)

1. Problem of Display with wrong spelling on 'ALBUM' or 'TRACK' mode.

Upgrade Procedure

Step 1 Check your current version

First check your current firmware version to see if you need to upgrade:

1. Keep no disc in DVD tray.
2. Press <STOP>, <1>, <2>, <3> on the Remote Control.
3. Compare the version shown on screen with this firmware upgrade version, **VER 0805 I**.
If different proceed to **step 2**, otherwise no upgrade necessary.

Step 2 Download Firmware upgrade

Click the link to save the software on your computer.

Step 3 Burning Upgrade on CD-R / CD-RW

1. Extract the files by unzipping the zipped file. (**Do not rename the filename**)
2. Write the extracted files – not the zip file – onto a blank CD-R or CD-RW disc, using the following settings:
 - File System CD-ROM Joliet
 - File name length : max 31 chars (ISO Level 2)
 - Mode : 2/XA
 - Character set : ASCII
 - Single session
 - Write Speed : Low
3. Finalized the disc. (The application may do this automatically.)

Tip: For more information on burning software we refer to two popular burning software programs

www.nero.com
www.easycdcreator.com

Step 4 Apply Upgrade to your Set

1. Power up the set and open the DVD tray.
2. Insert the prepared upgrade CD-ROM.
3. Close the tray and the set will auto read the disc.
4. Upon recognize the disc, the set will start to download the new firmware. The TV screen will show the following messages in sequence :
"Disc reading" "Erase" "Writing" "Done" "Open"
5. The whole process takes less than 2 minutes after which the set shuts down automatically and the TV screen becomes dark.
Note: Do not press any buttons or interrupt the mains supply during the entire upgrading process, otherwise the set may become defective.
6. Unplug & replug the mains cable
7. Press **"Open"** key directly and remove Upgrade CD-ROM.

Your product is successfully upgraded!

Firmware upgrade history

Firmware Version 0805 I

Release Date 4 November 2005

This upgrade software solves the problem of Display with wrong spelling on '**ALBUM**' or '**TRACK**' mode.