



Clock radio

Easy alarm time set

- Large LED display (for /17)
- Wake up to radio or buzzer
- 24 hour alarm reset
- Repeat alarm
- Sleptimer
- FM/MW or FM/LM tuner
- Battery back-up



Let's make things better.



PHILIPS



Clock radio

Standard product information

Clock/ alarm

- Electronic clock
- Quartz - operated clock /14
- Wake up by radio or buzzer
- Alarm Single alarm, sleeptimer function, repeat alarm (9 minutes)
- Time/alarm setting Hours/minutes

Tuner

- FM/AM tuning
- Wavebands
/04 FM/LW
/00, /05, /09, /14 FM/MW
/17 FM/AM
- Frequency ranges FM 87.5 - 108 MHz
 MW 525 - 1607 kHz
 LW 148.5 - 284 kHz
 AM 530 - 1710 kHz

Amplifier

- Max output power (RMS) (+1 dB ; D < 10%) 80 m Watts

Sound system

- Loudspeaker 64 mm (2.5")

Display

- Red LED 0.9" (22.5 mm) digit height for /17
- Red LED 0.6" (15mm) digit height for /00, /04, /05, /09

Power supply

- AC Mains
/17 120V, 60Hz
/00, /04, /05, /09 230V, 50 Hz
- Backup battery 6F22, 9V (not included)

General

- Material Polystyrene
- Weight 0.5 kg
- Dimensions (mm) 180 W x 43 H x 162 D
- Quantity/mastercarton 6

Easy alarm/ time set

Wake up to radio or buzzer

Gives you the choice of waking up to your favourite radio station or alarm buzzer.

24 hour alarm reset

Automatically resets the alarm for the same time on the next day, so you don't have to keep manually resetting the alarm.

Repeat alarm

Switches off the alarm for 9 minutes.

FM/MW or FM/LM tuner

Sleeptimer

Battery back-up

Printed in Hong Kong 2000-12-01
Specifications subject to modification without notice
© 2000 Koninklijke Philips Electronics N.V.
All rights reserved

<http://www.philips.com>

Let's make things better.



PHILIPS